

# TRACK CONNECTORS












## 120V Track System

# WAC LIGHTING

Responsible Lighting®



Location: \_\_\_\_\_

Track Connectors	Model	Finish	Description	
Live End Connector 	<b>HLE</b> H Track	<b>BK</b> Black <b>BN*</b> Brushed Nickel <b>WT</b> White <b>DB**</b> Dark Bronze	Use for direct wiring through ceiling. A canopy plate is required when using with a standard junction box.	
	<b>LLE</b> L Track			4¼" × 1⅜" × ¾"
	<b>JLE</b> J Track			4¾" × 1¼" × ¾"
	<b>J2-LE</b> J2 Track			4¾" × 1¼" × ¾"
Live End BX Connector 	<b>HBXLE</b> H Track		6" × 1⅜" × 1¼"	Use with surface mounted BX or non-metallic sheathed cable. Also provides through the ceiling connection.
	<b>LBXLE</b> L Track		5¾" × 1⅜" × 1¼"	
	<b>JBXLE</b> J Track		6¼" × 1⅜" × 1¼"	
	<b>J2-BXLE</b> J2 Track		5⅞" × 1⅜" × 1¼"	
"I" Power Connector 	<b>HI-PWR</b> H Track		6¾" × 1⅜" × ¾"	Power entry point at the connection of 2 tracks.
	<b>LI-PWR</b> L Track		7" × 1⅜" × ¾"	
	<b>JI-PWR</b> J Track		7⅞" × 1⅜" × ¾"	
	<b>J2-IPWR</b> J2 Track		7" × 1⅜" × ¾"	
"L" Connector Left 	<b>HL-LEFT</b> H Track		2¾" × 2¾" × ¾"	Use to join 2 track sections to make power feedable 90° left polarity turns.
	<b>LL-LEFT</b> L Track		4¼" × 4¼" × ¾"	
	<b>JL-LEFT</b> J Track		4¼" × 4¼" × ¾"	
	<b>J2-LLEFT</b> J2 Track		4¼" × 4¼" × ¾"	
"L" Connector Right 	<b>HL-RIGHT</b> H Track	2¾" × 2¾" × ¾"	Use to join 2 track sections to make power feedable 90° right polarity turns.	
	<b>LL-RIGHT</b> L Track	4¼" × 4¼" × ¾"		
	<b>JL-RIGHT</b> J Track	4¼" × 4¼" × ¾"		
	<b>J2-LRIGHT</b> J2 Track	4¼" × 4¼" × ¾"		
"T" Connector 	<b>HT</b> H Track	4" × 2¾" × ¾"	Use to join 3 track sections. Power feedable on H and J only. "T" Connector with opposite polarity can be custom ordered.	
	<b>LT</b> L Track	7¼" × 4¼" × ¾"		
	<b>JT</b> J Track	7⅞" × 4¼" × ¾"		
	<b>J2-T</b> J2 Track	7" × 4¼" × ¾"		
"X" Connector 	<b>HX</b> H Track	4⅞" × 4⅞" × ¾"	Use to join 4 track sections. Power feedable on H and J only.	
	<b>LX</b> L Track	7⅞" × 7⅞" × ¾"		
	<b>JX</b> J Track	7⅞" × 7⅞" × ¾"		
	<b>J2-X</b> J2 Track	7" × 7" × ¾"		
"I" Connector 	<b>HI</b> H Track	3" × 1⅜" × ¾"	Use to join two sections of track with electrical continuity.	
	<b>LI</b> L Track	3⅞" × 1⅜" × ¾"		
	<b>JI</b> J Track	3" × 1⅜" × ¾"		
	<b>J2-I</b> J2 Track	4½" × 1⅜" × ¾"		
"I" Dead End Connector 	<b>HI-DEC</b> H Track	3" × 1⅜" × ¾"	Joins two sections of track without electrical continuity.	
	<b>LI-DEC</b> L Track	3⅞" × 1⅜" × ¾"		
	<b>JI-DEC</b> J Track	3" × 1⅜" × ¾"		
	<b>J2-IDEC</b> J2 Track	3½" × 1⅜" × ¾"		
Flexible Track Connector 	<b>HFLX</b> H Track	11" × 1⅜" × ¾"	Connects two track sections at variable angles. Use as a transition from wall-to-wall, wall-to-ceiling, or ceiling-to-ceiling. Power feedable.	
	<b>LFLX</b> L Track	9¾" × 1⅜" × ¾"		
	<b>JFLX</b> J Track	8½" × 1⅜" × ¾"		
	<b>J2-FLX</b> J2 Track	11½" × 1⅜" × ¾"		
Floating Canopy Connector 	<b>HFC</b> H Track	4½" × 4½" × 1½"	Connects to octagon box. Allows track to be powered anywhere along the length of the track.	
	<b>LFC</b> L Track	4¼" × 4¼" × 1⅜"		
	<b>JFC</b> J Track	4⅝" × 4⅝" × 1⅜"		

\*BN finish only available for H, L, J Track \*\*DB finish only available for H Track