

90+ LIGHTING



MODEL	PAR20 7W 500LM 2700K E26
SKU	SE-RC11.1407G

DIMMER COMPATIBILITY LIST					
MANUFACTURER	BRAND	DIMMER MODEL	COMPATIBILITY		
LUTRON	DIVA	DV-603P	OK		
		DVW-600PH-WH	NC		
		DV-603PH-WH	OK		
		DV-600PH-WH	OK		
		DVCL-153PH	NC		
		DV-603PH-WH	OK		
		DVCL-153P-WH	OK		
		DV-600P-WH	NC		
		DVWCL-153PH-WHC	OK		
		DVCL-253PH	NC		
		DVCL-153P-WH	OK		
		DVELV-300P-WH	OK		
	DIVA C+L	DVWCL-153PH-WH	OK		
	-	S-600	NC		
	SKYLARK	-	CTCL-153P-WH	OK	
		-	S-600PR-WH	OK	
		-	S-603PGH-WH	NC	
		-	S-600H-WH	NC	
		-	S-10PH	NC	
		-	SCL-153P-WH	NC	
		-	S-600-IV	OK	
		-	S-600-AL	OK	
		-	S-603PH-WH	OK	
		-	S-600P-WH	NC	
		-	SCL-153PH-WH	OK	
		-	S-603P-WH	OK	
		-	SELV-300P-WH	OK	
		-	SLV-600-WH	OK	
		-	D-600PH-DK	NC	
		-	MAW-600	NC	
		MAESTRO	-	MAW-600H-AL	NC
			-	MACL-153M-WH	NC
	-		MACL-153MR-WH	NC	
	-		MACL-153MH-WH	NC	
	-		MSCL-OP153MH-WH	NC	
	-		MACL-153MLH-WH	NC	
	-		TG-603PGH-WH	NC	
	-		MAELV-600-WH	OK	
	-		DV-603PR	OK	
	-		D-600RH-DK	NC	
	TOGGLER	-	TG-600PH-WH	OK	
		-	TG-600PH-IV	NC	
		-	TGCL-153PH-WH	OK	
		-	D-600R-WH	OK	
	-	D-600R-IV	NC		
	ARIADNI	-	AYCL-153P-WH	OK	
		-	AY-600PH-WH	NC	
		-	AYCL-153PH	OK	
	VIVE	MRF2S-6CL-WH	OK		
	CASETA	PD-6WCL-WH	OK		
	SPACER	SPSELV-600M	OK		
	NOVA T	NTELV-300-WH	OK		
	-	NTLV-600-277-WH	OK		
	RADIO RA2	RRD-6CL-WH	OK		
	DECORA	R62-6674-P0W	OK		
	LEVITON	-	6684	NC	
		-	NO.6683	NC	
		-	6631-LA	OK	
		-	IPI06	NC	
		-	S-600P-WH	OK	
-		NO.6672	OK		
-		603-6631-A	OK		
-		6631-A	OK		
-		NO.IPL06	NC		
-		IPI10-1LZ	NC		
-		6683-10Z	NC		
-		IPI06-1LZ	OK		
-		NO.6631	OK		
-		6681	NC		
-		S-600P-WH	OK		
-		18024	OK		
GE		-	LUXDM600-12	OK	
ALMOND		-	DM600-12-3	OK	
CTL		-	SDM3/1000	OK	
AH		-	SDM/600	NC	
LEGRAND	-	HCL453PTC	NC		
COOPER	-	DAL06P-C2-K	NC		
	-	TAL06P-C2-K	NC		
	-	SAL06P-W-K	NC		
MAXXIMA	-	AAL06-C1	NC		
	-	MEW-DM600	OK		

DIMMER COMPATIBILITY

OK	Dims to < 15%
OK	Dims to 15 - 30%
NC	Not Compatible

90+ LIGHTING NOTES

- 1) This dimmer compatibility chart is provided by 90+ Lighting as a guidance for selecting a dimmer and lamp combination.
 - 2) The results may be different for each application depending on the installation conditions.
 - 3) 90+ Lighting recommends to perform a previous test before the installation to verify the dimmer compatibility.
 - 4) We recommend using a 1/5 loading factor for incandescent dimmers when using with 90+ lamps.
- For example: a 400W dimmer should be loaded with a number of lamps whose combined power do not exceed 80W.