



S29752

60W/LED/HID/MB/5000K/100-277V/EX39
 60 watt - LED HID Replacement; 5000K; Mogul extended base;
 Adjustable beam angle; 100-277 volts

Features

- Replaces HID, CFL, and Incandescent
- Direct wire range voltage 100-277V
- Approved for totally enclosed fixtures
- Hi bay, low bay and post top
- Light panels lock into place creating 3 separate beam angle options
- IP65 rated
- 5 year limited warranty



S29752

Specification note: Power Factor >0.9; Operating temperature range -20°C to 65°C; Operating Frequency 50-60Hz; Working Voltage AC 90-305V

Optional accessory: In-line surge protector 80-929

Width (360°)	Width (270°)	Width (180°)
3.8"	8.2"	9.3"

Minimum Compartment Size		
Length	Width	Depth
8.27 inch	9.25 inch	9.25 inch

Item Number	Product Line	UPC	Input Voltage	Watts	Incandescent Equivalent	Fluorescent Equivalent	HID Equivalent
S29752	Hi-Pro	045923297526	100 - 277	60	500W	85W	250W

Power Factor	Base	ANSI Base	Lamp Code	Dimmable/Non-Dimmable	Finish	MOL In Inches	MOD In Inches
0.90	Mogul Extended	EX39	60W/LED/HID/MB/5000K/100-277V/EX39	Non-Dimmable	White	7.87"	3.82" (Open 9.31")

Initial Lumens	Average Rated Hours	Kelvin Temp	Color	CRI	Beam Spread Deg	Operating Temperature	Pack
----------------	---------------------	-------------	-------	-----	-----------------	-----------------------	------

7800	50000	5000	Stark White	80+	Adjustable: 360; 270; 180	-20C (-4F) to a maximum of +65C (+149F)	12/6
Package Type	RoHS Compliant	Fixture Type	UL Classification		Warranty	Thermal Management	
Box	Yes	Enclosed Rated	cULus - Wet Location Rated		5 Year Limited	More Details About*	

*Hi-PRO lamps are manufactured with a new Thermal Management circuit design (Temperature Control). If the lamp heats up in an application to 110°C, it will automatically reduce itself to 70% of rated wattage. If the ambient temperature continues to increase and reaches 120°C, it will reduce itself to 50% of rated wattage. In the event this happens, the lamps will remain at that level until they are turned off at which time they will reset and come back on a full brightness.