

## I-880 2000 LUMEN EMERGENCY BALLAST

[SPECIFICATION PDF](#)
[INSTALLATION](#)


HIGH LUMEN  
OUTPUT



### LUMEN OUTPUT

- (1) Lamp - 2000 lumens
- (2) Lamps - 1000 lumens per lamp

### LAMPS OPERATED

Most 2'-8' single, bipin, T8 through T12 HO and VHO fluorescent lamps including long compact lamps and 2'-4' 28W and 54W T5 HO and VHO lamps

### EMERGENCY OPERATION

90 Minutes

The **I-880** Fluorescent Emergency Ballast allows the same fixture to be used for both normal and emergency operation. In the event of a power failure, the **I-880** switches to the emergency mode and operates **one or two** of the existing lamps for 90 minutes. The unit contains a battery, charger, and inverter circuit in a single can and can be mounted in the wireway or on top of the fixture. The **I-880** can be used with **most 2'-8' T8 thru T12 and 2'-4' 28W and 54W T5** fluorescent lamps, with an initial output of up to 2000 lumens for one or two lamps, and features lamp selector leads for optimizing light output for designated lamp types.

### PRODUCT ADVANTAGES

- 2000 lumen output
- [Time Delay Enhancement](#) (End-of-Lamp-Life)
- [Open Circuit Isolation](#)

### FEATURES

- Will cold start and
- Long-life high-temperature
- Galvanized steel construction
- Includes test switch
- For use with switchgear
- [5 Year Warranty](#) (See Spec Sheet)

Input Voltage (Dual) 120/277V 60Hz

Input Wattage 4.5 Watts

Lamps Operated Most 2'-8' single, bipin T8 thru T12 HO and VHO fluorescent lamps including long compact lamps and 2'-4' 28W and 54W T5 HO and VHO lamps