

[Return to search](#)

[Print Page](#)



**Product Number:** 29411  
**Order Abbreviation:** CF23EL/MINITWIST/2700K  
**General Description:** DULUX EL 23W Mini Twist Spiral compact fluorescent lamp with integral 120V ballast, medium screw base, 2700K, 82 CRI, packaged 6/carton.

Product Information	
Abbrev. With Packaging Info.	CF23ELMINITWIST2700K 6/CS 1/SKU
Average Rated Life (hr)	10000
Base	Medium
Bulb	MINI TWIST
Color Rendering Index (CRI)	82
Color Temperature/CCT (K)	2700
Family Brand Name	Dulux® EL
Initial Lumens at 25C	1600
Mean Lumens at 25C	1160
Maximum Overall Length - MOL (in)	5.75
Nominal Wattage (W)	23.00

Additional Product Information
<a href="#">Product Documents, Graphs, and Images</a>
<a href="#">Packaging Information</a>



**Footnotes**

- Approximate initial lumens after 100 hours operation.
- Minimum starting temperature for DULUX EL lamps is 0° F, unless otherwise specified in product literature. .
- DULUX ELs meet CSA, FCC and UL requirements.
- Caution: DULUX EL units cannot be used on dimming circuits (unless the lamp is labeled dimmable), emergency exit fixtures or lights, electronic timers, photocells, lighted switches or any other switches that do not meet UL20 Sec. 7.6.15. In outdoor applications, use only in enclosed fixtures to avoid exposure to weather. Use only on 120V, 60 Hz circuits. Never disassemble or modify lamp. Install or remove unit from fixture by grasping plastic base. Best performance achieved when operated at 77degrees F (25 degrees C). 40 Watt lamp is designed for base down orientation only
- The life ratings of fluorescent lamps are based on 3 hr. burning cycles under specified conditions and with ballast meeting ANSI specifications. If burning cycle is increased, there will be a corresponding increase in the average hours life.
- Minimum starting temperature for DULUX EL lamps is 0 degrees F
- Rule of Thumb for Compact Fluorescent Lamps: Divide wattage of incandescent lamp by 4 to determine approximate wattage of compact fluorescent lamp that will provide similar light output.

[Print Page](#)