



PX100, PX300 & PX600 Series Safety Transformers



These Safety Transformers are specifically designed to supply 12 volts to pool/spa lights, submersible fixtures and outdoor garden lights. A grounded shield between the primary and secondary windings assures safe operation and the built-in circuit protection will disconnect power to the transformer in case of defect or overload.

Applications

- Pool Lights
- Spa Lights
- Garden Lights
- Fountain Lights

Specifications - PX100/S, PX300/S

Enclosure – 7.25" (19.4 cm) H x 5.25" (13.3 cm) W x 4.5" (11.4 cm) D. Stainless steel or steel with electrostatically applied light beige finish. Mounting brackets top and bottom.

Knockouts – Total of ten combination 1/2"-3/4" knockouts, (2) right side, (2) left side, (2) back, (4) bottom.

Electrical Rating – See table.

Shipping Weight – See table.

Specifications – PX600/S

Enclosure – 10" (25.4 cm) high x 10" (25.4 cm) wide x 5" (12.7 cm) deep. Stainless steel or steel with electrostatically applied light beige finish. Mounting brackets top and bottom.

Knockouts – Two combination 1/2"-3/4", and 4 combination 3/4"-1" knockouts on the bottom. Total of six combination 1/2"-3/4" knockouts, (2) right side, (2) left side, (2) back.

Electrical Rating – See table.

Shipping Weight – See table.

| Model # | Description | Input | Output | Shipping Weight |
|---------|------------------------------------|------------|--------------|--------------------|
| PX100 | 100 Watt Beige Steel Enclosure | 120V, 1AMP | 12 or 13V | 7.0 lbs (3.2 kg) |
| PX100S | 100 Watt Stainless Steel Enclosure | 120V, 1AMP | 12 or 13V | 7.0 lbs (3.2 kg) |
| PX300 | 300 Watt Beige Steel Enclosure | 120V, 3AMP | 12,13 or 14V | 13.0 lbs (5.9 kg) |
| PX300S | 300 Watt Stainless Steel Enclosure | 120V, 3AMP | 12,13 or 14V | 13.0 lbs (5.9 kg) |
| PX600 | 600 Watt Beige Steel Enclosure | 120V, 6AMP | 12,13 or 14V | 26.0 lbs (11.7 kg) |
| PX600S | 600 Watt Stainless Steel Enclosure | 120V, 6AMP | 12,13 or 14V | 26.0 lbs (11.7 kg) |



PX100



PX100S



PX300



PX300S



PX600



PX600S