1-800-624-4488




# GE Lighting

## 22181 - F382D/835/4P

GE 2D® T6 - Facilities; Retail Display; Hospitality; Office; Restaurant; Warehouse







#### **CAUTIONS & WARNINGS**

Caution

- · Lamp may shatter and cause injury if broken
- Remove and install by grasping only plastic portion of the lamp.

**Customer Name:** Project Name: Fixture Type:

## **GENERAL CHARACTERISTICS**

Lamp Type Bulb Base Wattage Rated Life Starting Temperature LEED-EB MR Credit

**Primary Application** 

Compact Fluorescent - Plug-In Τ6 GR10q-4 38 10000 hrs -10 °C (14 °F) 167 picograms Hg per mean lumen hour Facilities;Retail Display;Hospitality;Office;Restaurant;W

#### **PHOTOMETRIC CHARACTERISTICS**

Initial Lumens 2850 Mean Lumens 2395 Nominal Initial Lumens per Watt 75 3500 K **Color Temperature** Color Rendering Index (CRI) 82

#### **ELECTRICAL CHARACTERISTICS**

Current (max) Open Circuit Voltage Across Starter Preheat Voltage Current Crest Factor Supply Current Frequency

### DIMENSIONS

Maximum Overall Length (MOL) Nominal Length Base Face to Top of Lamp 8.1100 in(206.0 mm) 8.100 in(205.7 mm)

5.25 A

198 V

4.25 V

20000 Hz

1.7

1.250 in(31.8 mm)

## **PRODUCT INFORMATION**

Product Code Description Standard Package Standard Package GTIN Standard Package Quantity Sales Unit No Of Items Per Sales Unit No Of Items Per Standard Package UPC

043168981866

#### NOTES

• 10-watt, 16-watt and 28-watt 2D lamps may be operated in any position. 21-watt, 38-watt, 39-watt, and 55-watt 2D lamps must be used with the leg market (a) in the diagram below the bend (b), in order to avoid overheating the end of the cap marked (c).

• 4-Pin lamp minimum starting temperature is a function of the ballast. Most ballasts are rated with a minimum starting temperature of 50 degrees F (10 C). Ballasts are also available that provide reliable starting to 0 degrees F (-18C) and -20 F (-29C).

Based on 60Hz reference circuit.

• Fluorescent lamp lumens decline during life