




BERGEN INDUSTRIES, INC.

B-Lite at a glance

- Labor saving unit comes fully assembled
- Multi-Tap ballast: 120v, 208v, 240v, 277v (factory wired 120v)
- 400w, clear MH Pulse Start lamp (included) meets OSHA1926.56 for minimum illumination of work areas (minimum of 5 foot-candles for general construction area lighting) when mounted 15' above 40' x 40' & 60' x 60' bays

B-Lite®

Features



Two .75" knockouts for conduit access. (One knockout on opposite side) for "daisy chain" of multiple fixtures

Steel housing, white powdercoat finish

Open air ballast housing to reduce temperature & overheating

Type "O" spring loaded PINK porcelain screw shell socket

3ft. power cord #18/3 SJTOW with NEMA 5-15120V, 15amp plug

400W MH Pulse Start Type "O" Lamp

Heavy duty corrosion resistant welded steel safety cage

Open-Close bottom guard 9.45" opening for easy re-lamping



Cat# BLite-400PS

Easy Carry Handle

Snap Lock "Self Locking" Hook



- Meets **OSHA** requirements for minimum illumination of work areas when properly installed
- Meets **EISA 2007** for energy efficiency
- Meets **NEC 2005** and 2008 requirements



HIGH BAY WORK LIGHT

www.bergeninc.com

p.800.875.1846

f.800.875.9419