

TECHNICAL BULLETIN MERCURY VAPOR LAMP

Mercury Vapor HF250PD


ANSI Code: H37 Product Code: 70309

Full line product offering


Features: • Long life

Long life • Applications: Roadway, Landscape,
Nickel-plated base • Factory, Sports, Parking, Security


PERFORMANCE DATA			
Initial lumens at rated watts after 100 hours operation	13700	lm	
Mean lumens at 10 hours/start	11179	lm	
Rated average life	24000	h	
Warm up time (90% lumens)	4	min	
Correlated color temperature	4100	K	
CIE chromaticity	0.375, 0.367	X ,Y	
Color rendering index	40		
Operating Position	Universal		
Time to hot re-start	10 max.	min	





Rugged construction



ELECTRICAL CHARACTERISTICS			
Nominal lamp wattage	250	W	
Nominal lamp voltage	130	V	
Nominal lamp current	2.1	Arms	
Current crest factor	2.0 Max.		
Ballast requirements			
Open circuit voltage	225	Vrms	
-30°C (-22°F)	318	Vpeak	
Min. starting current	2.1	Arms	
Max. starting current	4.5	Arms	







ISO 9001:2008 Certified ISO 14001:2004 Certified OHSAS 18001:2007 Certified ISO 17025:2005 Accredited



Address: 9150 Hendricks Rd., Mentor, OH 44060
Phone: 888-665-2677 Fax: 800-811-7395 E-Mail: sales@eyelighting.com
Phone: (440) 350-7000 Fax: (440) 350-7001 www.eyelighting.com



TECHNICAL BULLETIN MERCURY VAPOR LAMP

AWARNING

This lamp can cause serious skin burn and eye inflammation from short-wave ultraviolet radiation if outer envelope of the lamp is broken or punctured. Do not use where people will remain for more than a few minutes unless adequate shielding or other safety precautions are used. Lamps that will automatically extinguish when the outer envelope is broken or punctured are commercially available.

RISK OF ELECTRIC SHOCK

•Turn power off before inspection, installation or removal •Protect lamp from direct contact with liquids to avoid breakage from thermal shock

RISK OF FIRE

•Keep combustible materials away from lamp during operation

UNEXPECTED LAMP RUPTURE MAY CAUSE INJURY, FIRE, OR PROPERTY DAMAGE

•Do not exceed rated ballast voltage •Do not use lamp if outer glass is scratched or broken. •Do not use beyond rated life •Do not turn on lamp until fully installed •Use only with a fixture and ballast rated for this product •Turn lamp off at least once a week for 15 minutes •Electrically insulate any metal to glass support in fixture

ACAUTION

RISK OF BURN

Allow lamp to cool before handling.

LAMP MAY SHATTER AND CAUSE INJURY

•Do not use excessive force when installing lamp •Dispose of lamp in a closed container

LAMP OPERATING INSTRUCTIONS

This is a discharge lamp and requires some time to restart and come up to full brightness after a power interruption. If power supply dips or is interrupted, lamps may extinguish and not restart. Turn off power supply for 10-15 minutes and allow lamp to fully cool. Lamp will restart when power is restored.

R Conforms to: USA: 21CFR1040.30 Canada: ANSI 136.1-2000

Hg) - LAMP CONTAINS MERCURY. Manage in Accord with Disposal Laws. See: www.lamprecycle.org or 1-888-665-2677.

 ϵ

ISO 9001:2008 Certified ISO 14001:2004 Certified OHSAS 18001:2007 Certified ISO 17025:2005 Accredited



Address: 9150 Hendricks Rd., Mentor, OH 44060
Phone: 888-665-2677 Fax: 800-811-7395 E-Mail: sales@eyelighting.com
Phone: (440) 350-7000 Fax: (440) 350-7001 www.eyelighting.com