



**20444 – F40/30BXSPX30-36**

GE Biax® T5 - Facilities; Retail Display; Hospitality; Office; Restaurant; Warehouse

 High Color Rendering  
Energy Savings

**GENERAL CHARACTERISTICS**

Lamp type	Compact Fluorescent - Plug-In
Bulb	T5
Base	4-Pin (2G11)
Wattage	40
Voltage	120/126
Rated Life	20000 hrs
Starting Temperature (MIN)	10 °C (50 °F)
LEED-EB MR Credit	176 picograms Hg per mean lumen hour
Primary Application	Facilities; Retail Display; Hospitality; Office; Restaurant; Warehouse

[View Larger](#)**PHOTOMETRIC CHARACTERISTICS**

Initial Lumens	3150
Mean Lumens	2840
Nominal Initial Lumens per Watt	78
Color Temperature	3000 K
Color Rendering Index (CRI)	82

**ELECTRICAL CHARACTERISTICS**

Lamp Current	0.320 A
Current Crest Factor (MAX)	1.7

**DIMENSIONS**

Maximum Overall Length (MOL)	22.5000 in (571.5 mm)
Nominal Length	22.500 in (571.5 mm)

**PRODUCT INFORMATION**

Product Code	20444
Description	F40/30BXSPX30-36
ANSI Code	60901-IEC-6240-2
Standard Package	Case
Standard Package GTIN	10043168204443
Standard Package Quantity	36
Sales Unit	Unit
No Of Items Per Sales Unit	1
No Of Items Per Standard Package	36
UPC	043168204446

**COMPATIBLE GE BALLASTS**

Product	# of	Power	Ballast
---------	------	-------	---------

**ADDITIONAL RESOURCES**

[Catalogs](#)  
[Testimonials](#)  
[Disposal Policies & Recycling Information](#)

Code	Description	Bulbs	Factor	Factor
<a href="#">80683</a>	C240PUNVHP-B-IP	1	95.0	1.0
<a href="#">80680</a>	C240SI120RH-IP	1	90.0	1.02
<a href="#">80681</a>	C240SI277RH-IP	1	90.0	1.02
<a href="#">80690</a>	C340SI120RH-IP	2	90.0	0.99
<a href="#">80691</a>	C340SI277RH-IP	2	90.0	0.99
<a href="#">87625</a>	GEM2FT40RS120	2	98.0	1.0

#### CAUTIONS & WARNINGS

[See list of cautions & warnings.](#)

#### NOTES

- 4-Pin lamp minimum starting temperature is a function of the ballast. Most ballasts are rated with a minimum starting temperature of 50 degrees F (10 C). Ballasts are also available that provide reliable starting to 0 degrees F (-18C) and -20 F (-29C).
- Based on 60Hz reference circuit.
- Fluorescent lamp lumens decline during life
- Life ratings based on rapid start operation. On instant start ballast, life rating is 25% lower.