



## SORAA LED MR16 Magnetic Transformer & Dimmer Compatibility

### Combined Transformers & Dimmers, North America

TRANSFORMERS		DIMMERS						
		Lutron Grafik Eye 3000	Lutron Skylark SLV-600P	Lutron DVLV-600P	Lutron Ceana CNLV-600P	Lutron Radio RAZ RRD-6NA 600W	Lutron Radio RAZ RRD-10D 800W	MARLIN CONTROLS Stellar DIMMING CABINET P/N 6-3-08-20-3-103T with RMS
Cooper	TF-149911	11%	F	F	F	NT	NT	7%
Cooper	TF 149911-TP 120	10%	F	F	F	NT	NT	9%
Linea	701970	13%	F	F	F	NT	NT	9%
Hasler Electric	MI-5481E	10%	F	F	F	NT	NT	9%
Juno	310-1333	13%	F	F	F	NT	NT	10%
Orientronic	DLR1250BN	13%	27%	27%	27%	NT	NT	8%
Q-TRAN	QT-50-75CK-PT-RC Date 11/11	10%	23%	23%	23%	NT	NT	1 lamp: F 2,3 lamps: 10%
Q-TRAN	QT50SV-120/12-RC	13%	30%	30%	30%	NT	NT	NT
Q-TRAN	QT20-120/12-TP-RC	9%	28%	28%	28%	NT	NT	9%
Q-TRAN	QT10-120/12-TP-RC	9%	24%	24%	24%	NT	NT	8%
Hammond Manufacturing	166Q12	13%	F	F	F	NT	NT	10%
Q-TRAN	Q6S-DC-120-12 (Rectified)	13%	21%	21%	21%	NT	NT	10%
Q-TRAN	QTM60-DC+CAP (Rectified + Filtered_	10%	F	F	F	NT	NT	1 lamp: F 2,3 lamps: 24%
MDL Corp	315-0071A – IRIS RPN3MR Fixture Normal Tap	NT	27%	33%	NT	9%	10%	NT
MDL Corp	315-0071A – IRIS RPN3MR Fixture dimmerl Tap	NT	28%	35%	NT	NT	NT	NT
MDL Corp	315-0126 – 12.3V	NT	26%	32%	NT	9%	8%	NT

Updated 12/19/13

Key **XX%** = Low dimming Range **F**= Fail **NT**= Not Tested