



**MR16 6W**

## Magnetic Dimmer Switch Compatibility

Brand	Series	Model	Load	Dimmability (# of lamps)																													
				HALO CAN				ELCO CAN					NORA CAN			JUNO CAN		ELG transf.						ESBCO transf.									
				H1499ICAT H36LVRTAY H1499TAT H149RTAT				EL1499ICA EL1499S EL1499 EL1499R					NLR- 404/75/277V			TC44R IC44N		BBC1ZA-B02XCI-2500X						1105-12 (300W)									
				1	2	3	4	1	2	3	4	5	1	2	3	1	2	1	2	3	4	5	6	1	2	3	4	5	6				
<b>LUTRON</b>	Diva	DVLV-600P	600	OK																													
	Abella	ABLV-1000M	600	X	OK				X	OK				20-100%	OK				X	20-100%				X	OK				35-100%	OK			
	Maestro	MALV-600	600	X					X	OK				X					X	OK				X					X				
		MALV-1000	1000	X					X	OK				X	20-100%				X	20-100%				25-100%	OK				X	OK			
	Lyneo LX	LXLV-600PL	600	25-100%				15-100%					15-100%			25-100%		15-100%						15-100%									
	Skylark	SLV-600P	600	25-100%				10-100%					15-100%			25-100%		10-100%						10-100%									
Toggler	TGLV-600PR	600	OK				OK					OK			OK		OK						25-100%										
<b>LEVITON</b>	Sure Slide	6613-PLA	600	25-100%				15-100%					15-100%			25-100%		15-100%						30-100%									
	Vizia +	VPM10-1LZ	600	25-100%				20-100%					15-100%			25-100%		25-100%						30-100%									
<b>COOPER</b>	Aspire	9536WS	1000	X																													

**Table Key**  
**OK= Fully compatible**  
 \_\_-\_\_% = Compatible within this range, flicker outside the range  
**X= Incompatible**

\*PLT has provided this dimmer switch compatibility chart for guidance when selecting a dimmer and lamp combination. Our lamps were tested for compatibility with the above listed dimmers. Dimmers that do not appear on the chart might still be compatible but have not been tested. All testing has been performed with a stable main supply. The quality of the local main, existing installation and wiring, as well as different manufacturer versions of the above dimmers and transformers may affect dimming performance. Since no assurance can be provided regarding these factors, it is a general recommendation to perform a test on-site prior to installing the LED lamps.



**MR16 6W**

### Electronic Dimmer Switch Compatibility

Brand	Series	Model	Load	Dimmability (# of lamps)																																					
				Hatch												Lightech						ELCO				WAC		SATCO													
				RS 12-60M						RS 12-80M						RS 12-60M (LED)						LRT60						Track				Track		Track							
				1	2	3	4	5	6	1	2	3	4	5	6	1	2	3	4	5	6	1	2	3	4	5	6	1	2	3	4	1	2	1	2						
LUTRON	Skylark	SELV-300P	300	OK						OK						OK						25-100%						OK						Flickers at 35%				X		OK	
	Diva	DVELV-300P	300	OK						OK						OK						25-100%						OK						Flickers at 50%				X		OK	
LEVITON	Sure Slide	6615-P0W	300	OK						OK						X						OK						OK				X				X		OK			

**Table Key**  
 OK= Fully compatible  
 \_\_-\_\_% = Compatible within this range, flicker outside the range  
 X= Incompatible

\*PLT has provided this dimmer switch compatibility chart for guidance when selecting a dimmer and lamp combination. Our lamps were tested for compatibility with the above listed dimmers. Dimmers that do not appear on the chart might still be compatible but have not been tested. All testing has been performed with a stable main supply. The quality of the local main, existing installation and wiring, as well as different manufacturer versions of the above dimmers and transformers may affect dimming performance. Since no assurance can be provided regarding these factors, it is a general recommendation to perform a test on-site prior to installing the LED lamps.