



Titanium Series T8 15W, 12W, 8W DIR
 For models: 15T8/4F/xxx/DIR, 12T8/4F/xxx/DIR, 8T8/2F/xxx/DIR
 Where xxx means 824-965 which indicates CRI and color temperature

Electronic Ballast Compatibility

| Series | Model | Type | Compatibility |
|-----------------------|-----------------------|------|---------------|
| Philips - Advance | ICN-1P32-N | IS | OK |
| Philips - Advance | ICN-2P32-N | IS | OK |
| Philips - Advance | ICN-3P32-N | IS | OK |
| Philips - Advance | ICN-4P32-N | IS | OK |
| Philips - Advance | IOPA-1P32-LW-N | IS | OK |
| Philips - Advance | IOPA-2P32-LW-N | IS | OK |
| Philips - Advance | IOP-2P32-LW-N | IS | OK |
| Philips - Advance | IOP-4P32-LW-N | IS | OK |
| Philips - Advance | IOP-3P32-N | IS | OK |
| Philips - Advance | ICN-132-MC | IS | OK |
| Philips - Advance | REZ-2S32-SC | PS | OK |
| Philips - Advance | VEZ-132-SC | PS | OK |
| Philips - Advance | VEZ-2S32-SC | PS | OK |
| Philips - Advance | IZT-132-SC | PS | OK |
| Philips - Advance | IZT-2PSP32-SC | PS | OK |
| Philips - Advance | ILV-2S32-SC | PS | OK |
| Philips - Advance | IOPA-4P32-SC | IS | 277V ONLY |
| Philips - Advance | ICN-4P32-SC | IS | 277V ONLY |
| Philips - Advance | IOP-2P32HL-SC | IS | X |
| GE - Ultramax | GE232MAX-L/ULTRA | IS | OK |
| GE - Ultramax | GE232MAX-N/ULTRA | IS | OK |
| GE - Ultramax | GE232MAX-H/ULTRA | IS | OK |
| GE - Ultramax | GE232MAXP-N/ULTRA | IS | OK |
| GE - Ultramax | GE232MAXP-H/ULTRA | IS | OK |
| GE - Ultramax | GE332MAX-N/ULTRA | IS | OK |
| GE - Ultramax | GE332MAX-H/ULTRA | IS | OK |
| GE - Ultramax | GE432MAX-L/ULTRA | IS | OK |
| GE - Ultramax | GE432MAX-N/ULTRA | IS | OK |
| GE - Proline | GE-232MV-N | IS | OK |
| GE - Proline | GE-332MV-N | IS | OK |
| GE - Proline | GE-432-120-N | IS | OK |
| GE - Ultrastart | GE-232-120-PS-N | PS | OK |
| Universal - Triad | B132IUNVHP-N | IS | OK |
| Universal - Triad | B232IUNVHP-N | IS | OK |
| Universal - Triad | B332IUNVHP-N | IS | OK |
| Universal - Ballastar | B232PUS50-A | PS | OK |
| Plusrite | BAF232IS/MV | IS | OK |
| Plusrite | BAF432IS/MV | IS | OK |
| Howard | EP2/32IS/MV/MC/HE | IS | OK |
| Howard | EPL3/32IS/MV/SC/HE | IS | OK |
| Sylvania | QTP 4x32T8/UNV ISN-SC | IS | OK |
| Sylvania | QHE 2x32T8/UNV ISN-SC | IS | OK |
| Fulham | WHSG4-UNV-T8-IS | IS | OK |
| Utilitech | YZ-232 | IS | OK |
| EIKO - Powermaster | PM-2x32T8-UNV-IS-L | IS | OK |
| Espen | VE232MVHIPHE | IS | OK |
| Sola | E-758-F-232-SC | IS | X |

*GREEN CREATIVE has provided this ballast compatibility chart for guidance when selecting a ballast and lamp combination. Lamps were tested for compatibility with the above listed Instant Start (IS) and Programmed Start (PS) ballasts. Ballasts that do not appear on the chart might still be compatible but have not been tested. All testing has been performed with a stable main supply. The quality of the local main, existing installation and wiring, as well as different manufacturer versions of the above ballasts may affect lamp performance. Since no assurance can be provided regarding these factors, it is a general recommendation to perform a test on-site prior to installing the LED lamps.



Titanium Series T8 15W, 12W, 8W DIR

For models: 15T8/4F/xxx/DIR, 12T8/4F/xxx/DIR, 8T8/2F/xxx/DIR
Where xxx means 824-965 which indicates CRI and color temperature

Emergency Ballast Compatibility

| Brand | Model | Compatibility |
|----------|----------------|---------------|
| Bodine | B54 | OK |
| Bodine | B100 | OK |
| Bodine | B60 | OK |
| Bodine | LP550 | OK |
| Bodine | B30ST | OK |
| Bodine | LP600 | OK |
| Iota | I-32 | OK |
| Iota | I-320 | OK |
| Iota | I-232 | OK |
| Iota | ISL-54 | OK |
| Iota | ISL-540 | OK |
| Iota | ISD-80 | OK |
| Iota | I-162 | OK |
| Iota | ICE-80 | OK |
| Lithonia | PS1400QD | OK |
| Lithonia | PSQ500QD | OK |
| Lithonia | E1500 M12 | OK |
| Fulham | FH3-DUAL-450L | OK |
| Fulham | FH4-DUAL-700L | OK |
| Fulham | FH5-DUAL-1400L | OK |
| ALP | EFP 32GS | OK |

*GREEN CREATIVE has provided this emergency ballast compatibility chart for guidance when selecting an emergency ballast and lamp combination. Lamps were tested for compatibility with the above listed emergency ballasts. Emergency ballasts that do not appear on the chart might still be compatible but have not been tested. All testing has been performed with a stable main supply. The quality of the local main, existing installation and wiring, as well as different manufacturer versions of the above emergency ballasts may affect lamp performance. Since no assurance can be provided regarding these factors, it is a general recommendation to perform a test on-site prior to installing the LED lamps.