



GREENCREATIVE

Titanium Series PLL 17W DIR
 For models: 17PLL/xxx/DIR
 Where xxx means 824-965 which indicates CRI and color temperature

Electronic Ballast Compatibility

Series	Model	Type	Compatibility
Philips - Advance	VEZ-2TTS40-SC	IS	OK
Philips - Advance	ICN-1TTP40-SC	IS	OK
Philips - Advance	ICN-2TTP40-SC	IS	OK
Philips - Advance	ICN-3TTP40-SC	IS	OK
Philips - Advance	ICF-2S42-M2-LD	PS	OK
Sylvania	QHE 1x40DL/UNV ISN-SC	IS	OK
Sylvania	QHE 2x40DL/UNV ISN-SC	IS	OK
Sylvania	QTP 2x26/32/42CF/UNV DM	PS	OK
Sylvania	QHE 3x40DL/UNV ISN-SC	IS	OK
GE	GEC140MAX-A	IS	OK
GE	GEC240MAX-A	IS	OK
GE	GEC340MAX-A	IS	OK
Hatch	HC242PS/UV/D	PS	OK
Howard	EP2/42CF/MV/2	PS	OK
AC Electronics	EPQ-A40PBXS/L	IS	OK
Universal - Triad	C240PUNVHP-B	PS	OK
Universal - Triad	C242UNVME	PS	OK

*GREEN CREATIVE has provided this ballast compatibility chart for guidance when selecting a ballast and lamp combination. Lamps were tested for compatibility with the above listed Instant Start (IS) and Programmed Start (PS) ballasts. Ballasts that do not appear on the chart might still be compatible but have not been tested. All testing has been performed with a stable main supply. The quality of the local main, existing installation and wiring, as well as different manufacturer versions of the above ballasts may affect lamp performance. Since no assurance can be provided regarding these factors, it is a general recommendation to perform a test on-site prior to installing the LED lamps.



GREENCREATIVE

Titanium Series PLL 17W DIR

For models: 17PLL/xxx/DIR

Where xxx means 824-965 which indicates CRI and color temperature

Emergency Ballast Compatibility

Brand	Model	Compatibility
Bodine	B100	OK
Bodine	B60	OK
Bodine	LP550	OK
Bodine	B30ST	OK
Bodine	LP600	OK
Iota	I-32	OK
Iota	ISL-54	OK
Iota	ISL-540	OK
Iota	I-42-EM-R-J	OK
Lithonia	PS1400QD	OK
Lithonia	PSQ500QD	OK
Lithonia	E1500 M12	OK
Fulham	FH3-DUAL-450L	OK
Fulham	FH4-DUAL-700L	OK

*GREEN CREATIVE has provided this emergency ballast compatibility chart for guidance when selecting an emergency ballast and lamp combination. Lamps were tested for compatibility with the above listed emergency ballasts. Emergency ballasts that do not appear on the chart might still be compatible but have not been tested. All testing has been performed with a stable main supply. The quality of the local main, existing installation and wiring, as well as different manufacturer versions of the above ballasts may affect lamp performance. Since no assurance can be provided regarding these factors, it is a general recommendation to perform a test on-site prior to installing the LED lamps.