



GREENCREATIVE

PL EDGE Series PL V 6W DIR
 For models: 6PLV/xxx/DIR
 Where xxx means 818-965 which indicates CRI and color temperature

Electronic Ballast Compatibility

Brand	Model	Compatibility
Philips - Advance	ICF-2S13-M1-BS-QS	OK
Philips - Advance	ICF-2S18-M1-BS-QS	OK
Philips - Advance	ICF-2S18-H1-LD	OK*
Sylvania	QTP 1/2x13CF/UNV DM	OK
Hatch	HC213PS/UV/D	OK
Triad/Universal Lighting	C213UNVBES	OK
Triad/Universal Lighting	C213UNVME	OK
Triad/Universal Lighting	C218UNVME	OK
Howard Lighting	EP2/13CF/MV/2	OK
Howard Lighting	EP2/18CF/MV/2	OK
Fulham	RHA-UNV-213-C	OK**
WARNING		
DO NOT INSTALL LAMPS WITH THE FOLLOWING BALLASTS. DO NOT INSTALL LAMPS WITH BALLASTS NOT ON THIS LIST UNTIL COMPATIBILITY IS CONFIRMED WITH OUR TECHNICAL TEAM.		
Some older ballast versions can cause over heating and damage to lamp and fixture. In case of doubt about compatibility, please contact us: techsupport@greencreative.com		
Philips - Advance	REB-2S26M-BS	X
Philips - Advance	H-2B13-TP-BLS	X
Sylvania	QTP 2x26CF/UNV QS	X
Sylvania	QTP 2x26CF/UNV BS	X
Sylvania	QTP 2x26CF/UNV TS	X
Sylvania	QTP 2x26/32/42CF/UNV BM	X
Sylvania	QTP 2x26/32/42CF/UNV TM	X
Sylvania	QTP 1/2x18CF/UNV TS	X
Sylvania	QTP 1/2xCF/UNV BM	X
Sylvania	QTP 1/2xCF/UNV TM	X
Sylvania	M1/2-CF-B-M-UNIV	X
Sylvania	M2-CF-18-Q-S-277V	X
Sylvania	QT2x32/277V IS-SC	X
Universal - Triad	CBT213L-120S	X
Antron	CSD-132PBM	X
Fulham	LH1-277-L	X
AC Electronics	CSD-332PBM	X
AC Electronics	EST-A40PS	X
Standard	31003STD E1321-UV-S	X
Topaz	B2642UNV/ME-TPZ	X
Watran	DBC218MVRSN	X
Motorola	M1-CF-42-B-S-120	X
Robertson	RED2L10-277	X
Hatch	FR1800	X
Energy Savings	ES-1-CFH-42/32/26-UNV-C	X

* Not compatible with older versions of this ballast

** Compatible in 2-lamp installations only

*GREEN CREATIVE has provided this ballast compatibility chart for guidance when selecting a ballast and lamp combination. Lamps were tested for compatibility with the above listed electronic ballasts. Ballasts that do not appear on the chart might still be compatible but have not been tested. All testing has been performed with a stable main supply. The quality of the local main, existing installation and wiring, as well as different manufacturer versions of the above ballasts may affect lamp performance. Since no assurance can be provided regarding these factors, it is a general recommendation to perform a test on-site prior to installing the LED lamps.