



Titanium Series T8 13W 4FT. DIR, 10.5W 4FT. DIR, 8W 3FT. DIR, 8W 2FT. DIR

For models: 13T8/4F/xxx/DIR, 10.5T8/4F/xxx/DIR, 8T8/3F/xxx/DIR, 8T8/2F/xxx/DIR
Where xxx means 824-965 which indicates CRI and color temperature

Electronic Ballast Compatibility

Series	Model	Type	Compatibility (Ballasts are compatible with 120V & 277V unless otherwise noted)			
			1 lamp	2 lamps	3 lamps	4 lamps
Philips - Advance	ICN-1P32-N	IS	OK	-	-	-
Philips - Advance	ICN-2P32-N	IS	OK	-	-	-
Philips - Advance	ICN-3P32-N	IS	OK	-	-	-
Philips - Advance	ICN-4P32-N	IS	OK	OK	-	-
Philips - Advance	IOPA-1P32-N	IS	OK	-	-	-
Philips - Advance	IOP-2P32-LW-N	IS	OK	-	-	-
Philips - Advance	IOP-3P32-N	IS	OK	OK	-	-
Philips - Advance	IOPA-4P32-N	IS	OK	OK	-	-
Philips - Advance	IOPA-1P32-LW-N	IS	OK	-	-	-
Philips - Advance	IOPA-2P32-LW-N	IS	OK	-	-	-
Philips - Advance	IOP-4P32-LW-N	IS	OK	OK	-	-
Philips - Advance	IOPA-4P32-SC	IS	277V only	OK	-	-
Philips - Advance	IOP-3P32-HL-N	IS	OK	OK	-	-
Philips - Advance	ICN-4P32-SC	IS	OK	OK	-	-
Philips - Advance	ICN-132-MC	IS	OK	-	-	-
Philips - Advance	VEZ-132-SC	PS	OK	-	-	-
Philips - Advance	IZT-132-SC	PS	OK	-	-	-
Philips - Advance	IZT-2PSP32-SC	PS	OK	OK	-	-
Philips - Advance	REZ-132-SC	PS	OK	-	-	-
Philips - Advance	VEZ-2S32-SC	PS	-	OK	-	-
Philips - Advance	REZ-2P32-SC	PS	-	OK	-	-
Philips - Advance	REL-2P32-SC	IS	X	X	-	-
Philips - Advance	REL-2P32-RH-TP	IS	X	X	-	-
GE - Ultramax	GE132MAXP-N/ULTRA	IS	OK	-	-	-
GE - Ultramax	GE232MAX-L/ULTRA	IS	OK	-	-	-
GE - Ultramax	GE232MAX-N/ULTRA	IS	OK	-	-	-
GE - Ultramax	GE232MAX-H/ULTRA	IS	OK	-	-	-
GE - Ultramax	GE232MAXP-H/ULTRA	IS	OK	-	-	-
GE - Ultramax	GE232MAXP-N/ULTRA	IS	OK	-	-	-
GE - Ultramax	GE332MAX-N/ULTRA	IS	OK	OK	-	-
GE - Ultramax	GE332MAX-H/ULTRA	IS	-	OK	-	-
GE - Ultramax	GE332MAXP-L/ULTRA	IS	OK	OK	-	-
GE - Ultramax	GE332MAXP-N/ULTRA	IS	OK	OK	-	-
GE - Ultramax	GE332MAXP-H/ULTRA	IS	X	X	-	-
GE - Ultramax	GE432MAX-L/ULTRA	IS	OK	OK	-	-
GE - Ultramax	GE432MAX-N/ULTRA	IS	OK	OK	-	-
GE - Ultramax	GE432MAXP-L/ULTRA	IS	OK	OK	-	-
GE - Ultramax	GE432MAXP-H/ULTRA	IS	X	X	-	-
GE - Ultramax	GE432MAX-G-N	IS	OK	OK	-	-
GE - Proline	GE-232-MV-N	IS	OK	-	-	-
GE - Proline	GE-332-MV-N	IS	OK	-	-	-
GE - Ultrastart	GE-232-MV-PS-N	PS	OK	-	-	-
GE - Ultrastart	GE-232-MV-PS-H	PS	OK	-	-	-
Sylvania	QHE 2X32T8/UNV DIM-TC	PS	-	OK	-	-
Sylvania	QHE4X32T8/UNV PSN-SC	PS	OK	OK	-	-
Sylvania	QHE 2X32T8/UNV ISL-SC	IS	OK	OK	-	-
Sylvania	QHE 4X32T8/UNV ISL-SC	IS	OK	OK	-	-
Sylvania	QTP3X32T8/UNV ISN-SC	IS	OK	OK	-	-
Sylvania	QTP 4X32T8/UNV ISN-SC	IS	OK	OK	-	-
Espen	VE2P32MVHIPE	IS	OK	-	-	-
Espen	VE2P32MVHIPE	IS	OK	-	-	-
Espen	VE3P32MVHIPE	IS	OK	OK	-	-
Espen	VE4P32MVHIPE	IS	OK	OK	-	-
Espen	VE232MVHIPE	IS	OK	OK	-	-
Universal	B132IUNVHP-N	IS	OK	-	-	-
Universal	B232IUNVHP-N	IS	OK	-	-	-
Universal	B232PUNVHE-B	PS	OK	-	-	-
Universal	B232PUS50-A	PS	X	X	-	-
Universal	B332IUNVHP-A	IS	OK	OK	-	-
Universal	B432IUNVHP-A	IS	OK	OK	-	-
Powermaster	PM-2X32T8-UNV-IS-L	IS	OK	-	-	-
Powermaster	PM-3X32T8-UNV-IS-H	IS	277V only	OK	-	-
Powermaster	PM-4X32T8-UNV-IS-L	IS	277V only	OK	-	-
Plusrite	BAF332IS/MV	IS	OK	-	-	-
Plusrite	BAF232IS/MV/H	IS	OK	-	-	-
Plusrite	BAF232IS/MV	IS	OK	-	-	-
Premium	BB-T8/UNH-2X32	IS	-	OK	-	-
Premium	BB-T8/UVH-4X32	IS	277V only	OK	-	-
Howard	EPL3/32IS/MV/SC/HE	IS	OK	-	-	-
Howard	EP3/32IS/MV/MC/HE	IS	OK	-	-	-
Fulham	WHS33-UNV-T8-IS	IS	OK	-	-	-
Robertson	ISU232T8120	IS	120V only	-	-	-
Sola	E-758-F-232-SC	IS	X	-	-	-
Sunpark	U-2/32ISE	IS	OK	-	-	-
Tcp	E4P32PSUNVE	PS	OK	-	-	-

*GREEN CREATIVE has provided this ballast compatibility chart for guidance when selecting a ballast and lamp combination. Lamps were tested for compatibility with the above listed Instant Start (IS) and Programmed Start (PS) ballasts. Ballasts that do not appear on the chart might still be compatible but have not been tested. All testing has been performed with a stable main supply. The quality of the local main, existing installation and wiring, as well as different manufacturer versions of the above ballasts may affect lamp performance. Since no assurance can be provided regarding these factors, it is a general recommendation to perform a test on-site prior to installing the LED lamps.