



### Dimmer Compatibility Guide

PLEASE NOTE: Compatibility list is based upon testing conducted by the manufacturer in a lab simulated environment. Actual results may vary.

Product Family Name: 860386 **860387** 860388  
 Item Number: LED10A19/827/D-C **LED10A19/830/D-C** LED10A19/840/D-C  
 Ordering Code:

Lamps per Dimmer

	Manufacturer	Product	Model Number	Overall Rating	Recommended		Notes
					Minimum	Maximum Tested*	
Incandescent/Halogen (Triac/Phase Cut/Leading Edge Dimmers)	Leviton	IllumaTech	IPI06	Good	1	6	Minor flicker low end with 1-6 ,dims down to 1%
		SureSlide	6633-P	Good	1	6	Minor flicker low end with 1-6 ,dims down to 1%
		Vizia	VPI06-1LZ	Good	1	6	Minor flicker low end with 1-6 ,flicker HE with 1, dims down 1%
	Lutron	Toggle	TG-600	Good	1	6	Minor flicker low end with 1-6 ,dims down to 1%
		Diva	DV-600	Good	1	6	Minor flicker low end with 1-6 ,dims down to 1%
		Skylark	S-600	Good	1	6	Minor flicker low end with 1-6 ,dims down to 1%
		Maestro	MAW-600	Good	3	6	Minor flicker low end with 3-6,dims down to 10%
	Legrand	Titan	CD703-PW	Bad	1	6	Flicker LE with 1-6, flicker Med 3,flicker HE with 1,dims down to 1%
		Harmony	D703-PTC	Good	1	6	Minor flicker low end with 1-6 ,dims down to 1%
		Harmony	H703-PTC	Good	1	6	Minor flicker LE with 1-6, flicker HE with 1, dims down to 1%
CFL/LED	Leviton	IllumaTech	IPL06	Good	1	6	Minor flicker low end with 1-6
		Sureslide	6674	Good	1	6	Minor flicker low end with 1-6
		Decora	6672	Good	1	6	Minor flicker low end with 1-6
	Lutron	Skylark	CTCL-153	Best	1	6	Dims down to 10% with 1-6,need to adjust dialt at medium position
		Diva	DVCL-153PL	Best	1	6	Dims down to 10% with 1-6,need to adjust dialt at medium position
		Maestro	MACL-153MLH	Best	1	6	Need to set the low end trim at 10%
		Skylark	SCL-153P	Best	1	6	Dims down to 10% with 1-6,need to adjust dialt at medium position
	Legrand	Toggle	TGCL-153PH	Best	1	6	Dims down to 10%with 1-6,need to adjust dialt at medium position
		Radio RA	RA2RR-6CL-PD	Best	1	6	Need to set the low end trim at 10%
		Harmony	DCL453-PTC	Good	1	6	Flicker Med with 1,minor flicker LE with 2-6, dims down to 1%
Harmony		HCL453PTC	Bad	1	6	Flicker Med & HE with 1,minor flicker LE with 2-6, dims down to 1%	
Adorne Paddle		ADPD453LM2	Good	1	6	Flicker LE with 1 ,shimmer at LE with 2-6, dims down to 15%	
Electronic Low Voltage	Leviton	Vizia	VPE04	Good	1	6	Flicker LE with 1-6, dims down to 1%
		IllumaTech	IPE04	Good	1	6	Flicker LE with 1-6, dims down to 1%
		Decora	6615-P	Bad	1	6	Flicker LE with 1-2, dims down to 30%
	Lutron	Skylark Countour	CTELV-303P	Good	1	6	Flicker at Medium with 1-6,shimmer LE with 2-6,dims down to 1%
		Diva	DVELV-300P	Good	1	6	Flicker at Medium with 1-6,shimmer LE with 2-6,dims down to 1%
		Maestro	MAELV-600	Good	1	6	Flicker at LE with 1-6, dims down to 5%
		Skylark	SELVB-300P	Good	1	6	Flicker at Medium with 1-6,shimmer LE with 2-6,dims down to 1%
	Legrand	VIERTI	VTEL-600M-W	Good	1	6	Shimmer at LE with 1-6,dims down to 1%
		Scene Director	SCELV	Good	1	6	Flicker at LE with 1-6, dims down to 10%
Magnetic Low Voltage	Leviton	Vizia	VPM-06	Good	1	6	Minor flicker at LE with 1-6, dims down to 1%
		Decora	6613-P	Good	1	6	Minor flicker at LE with 1-6, minor flicker at Med with 1 ,dims down to 1%
	Lutron	Maestro	MALV-600	Bad	4	6	Minor flicker at LE with 4-6 ,dims down to 5%
		Harmony	DLV703-PW	Bad	1	6	Minor flicker at LE with 1-6, flicker at Med with 1-2 ,dims down to 1%
	Legrand	Titan	CDLV703-PW	Bad	1	6	Minor flicker at LE with 1-6, flicker at HE with 1-3, dims down to 1%
Universal	Legrand	Adorne SoftTap	ADTP703TU	Good	1	6	Shimmer at LE with 1-6, dims down to 5%
		Miro Decorator	DRD4-W	Good	1	6	Minor flicker at LE with 1-6, dims down to 1%
		Harmony	H703PTUTC	Good	1	6	Shimmer at LE with 1-6, dims down to 10%
		Adorne Whisper	ADWR700MMTUM2	Good	1	6	Minor flicker at LE with 1-6, dims down to 2%
	Cooper	Adorne Touch	ADTH700MMTUM2	Good	1	6	Minor flicker at LE with 1-6, dims down to 2%
		Decorator	DAL06P-C2-K-L	Good	1	6	Flicker at LE with 1-6, flicker at Med with 1-2, dims down to 1%
		Skye	SAL06P-W-K-L	Good	1	6	Flicker at LE with 1-6, dims down to 1%

\*Maximum Tested (Lamps per Dimmer) - Additional lamps may work with your dimmer system. For maximum capacity please consult dimmer manufacturer.

†May experience "pop-on", lights cannot be turned on immediately to their minimum level. The slider needs to be raised above the minimum light level for the lights to first turn on if they were initially off. Then, the slider can be lowered to get to a lower light level; the dimmer cannot be turned on to just the minimum level.

Overall Rating	
Not Compatible	One or more of the following observed: Major flickering at various points, significant audible noise, no dimming range, does not turn off.
Bad	One or more of the following observed: Some flickering observed at various points, audible noise may be present, dimming not smooth.
Good	One or more of the following observed: Minor flickering at some point may exist. Dead travel may exist, which means there may be periods of time when the slider (or other form of control button) is moved without affecting the light level. These periods of dead travel are minor and most of the time not visible. Minor audible noise.
Best	Most of the following observed: No flickering, minimal audible noise (typically less than 25 dBA), wide dimming range - can dim down to 20% or less of light output.
High End (H.E.) Dead Travel	Determines how much, if any, dead travel exists at the top and bottom of the dimmer's range. Dead travel is when the slider can be moved without affecting the light level.
Low End (L.E.) Dead Travel	