

Dimmer Compatibility Guide

PLEASE NOTE: Compatibility list is based upon testing conducted by the manufacturer in a lab simulated environment. Actual results may vary.

Product Family Name: Filamnets: Fully Compatible Dimming
Item Number: 776607 776665
Ordering Code: LED4T9L/22K/FIL-NOS/2 LED4T9L/27K/FIL/2

Lamps per Dimmer

	Manufacturer	Product	Model Number	Overall Rating	Lamps per Dimmer		Notes
					Recommended Minimum	Maximum Tested*	
Incandescent/Halogen (Triac/Phase Cut/Leading Edge Dimmers)	Leviton	IllumaTech	IPI06	Best	1	6	Minor hum LE to HE, dims down to 15%
		SureSlide	6633-P	Best	1	6	Minor hum LE to HE, dims down to 5%
		Vizia	VPI06-1LZ	Good	2+	6	Minor flicker at LE. Minor hum LE to HE, dims down to 15%
	Lutron	Toggler	TG-600	Best	1	6	Minor hum LE to HE, dims down to 10%
		Diva	DV-600	Best	1	6	Minor hum LE to HE, dims down to 1%
		Skylark	S-600	Best	1	6	Minor hum LE to HE, dims down to 1%
		Maestro	MAW-600	Good	1+	6	Minor flicker at LE, minor hum LE to HE, dims down to 10%
	Legrand	Titan	CD703-PW	Good	1	6	Minor flicker at LE and medium with 1-2, minor hum LE to HE, dims down to 25%
		Harmony	D703-PTC	Good	1	6	Minor flicker at LE and medium with 1-2, minor hum LE to HE, dims down to 1%
		Harmony	H703-PTC	Good	1	6	Minor flicker at LE and medium with 2, minor hum LE to HE, dims down to 5%
CFL/LED	Leviton	IllumaTech	IPL06	Best	1	6	Minor hum LE to HE, dims down to 1%
		Sureslide	6674	Best	1	6	Minor hum LE to HE, dims down to 15%
		Decora	6672	Best	1	6	Minor hum LE to HE, dims down to 15%
	Lutron	Skylark	CTCL-153	Best	1	6	Minor hum LE to HE, dims down to 1%
		Diva	DVCL-153PL	Best	1	6	Minor hum LE to HE, minor flicker after dims below 10%
		Maestro	MACL-153MLH	Best	1	6	Minor hum LE to HE, dims down to 5%
		Skylark	SCL-153P	Best	1	6	Minor hum LE to HE, dims down to 1%
		Toggler	TGCL-153PH	Best	1	6	Minor hum LE to HE, dims down to 1%
		Radio RA	RA2RR-6CL-PD	Best	1	6	Minor hum LE to HE, minor flicker after dims below 10%
	Legrand	Harmony	DCL453-PTC	Best	1	6	Minor hum LE to HE, dims down to 15%
		Harmony	HCL453PTC	Best	1	6	Minor hum LE to HE, dims down to 15%
		Adorne Paddle	ADPD453LM2	Bad	1	6	Minor hum LE to HE, dims down to 30%
		Electronic Low Voltage	Leviton	Vizia	VPE04	Good	1
IllumaTech	IPE04			Good	1	6	Minor flicker at medium 1-6, dims down to 15%
Decora	6615-P			Bad	1	6	Minor flicker at medium 1-6, dims down to 45%
Lutron	Skylark		SELVB-300P	Good	1	6	Minor flicker at medium 1-6, dims down to 15%
	Skylark Countour		CTELV-303P	Good	1	6	Minor flicker at medium 1-6, dims down to 15%
	Diva		DVELV-300P	Good	1	6	Minor flicker at medium 1-6, dims down to 15%
	Maestro		MAELV-600	Good	1	6	Minor flicker at medium 1-6, minor flicker at HE with 2, dims down to 15%
Magentic Low Voltage	Leviton	Vizia	VPM-06	Good	2+	6	Minor flicker at LE with 3-4, minor hum LE to HE, dims down to 15%
		Decora	6613-P	Good	1	6	Minor hum LE to HE, dims down to 10%
	Lutron	Maestro	MALV-600	Good	2+	6	Minor hum LE to HE, dims down to 15%
		Harmony	DLV703-PW	Good	1	6	Minor flicker at HE with 1-2, minor flicker at medium with 1, minor hum LE to HE
	Legrand	Titan	CDLV703-PW	Bad	1	6	Flicker at medium with 2, minor flicker medium and HE with 1, minor hum LE to HE
Universal	Legrand	Adorne SofTap	ADTP703TU	Best	1	6	Minor hum LE to HE, dims down to 20%
		Miro Decorator	DRD4-W	Not Compatible	1	6	Strobe at LE with 1-6
		Harmony	H703PTUTC	Best	1	6	Minor hum LE to HE, dims down to 15%
		Adorne Whisper	ADWR700MMTUW2	Best	1	6	Minor hum LE to HE, dims down to 1%
		Adorne Touch	ADTH700MMTUM2	Best	1	6	Minor hum LE to HE, dims down to 1%
	Cooper	Decorator	DAL06P-C2-K-L	Good	1	6	Minor flicker at medium with 1, minor hum LE to HE, dims down to 20%
		Skye	SAL06P-W-K-L	Good	1	6	Minor flicker at LE after dims below 15%, flicker at LE with 1 below 20%, minor hum LE to HE

*Maximum Tested (Lamps per Dimmer) - Additional lamps may work with your dimmer system. For maximum capacity please consult dimmer manufacturer.

†May experience "pop-on", lights cannot be turned on immediately to their minimum level. The slider needs to be raised above the minimum light level for the lights to first turn on if they were initially off. Then, the slider can be lowered to get to a lower light level; the dimmer cannot be turned on to just the minimum level.

Overall Rating	
Not Compatible	One or more of the following observed: Major flickering at various points, significant audible noise, no dimming range, does not turn off.
Bad	One or more of the following observed: Some flickering observed at various points, audible noise may be present, dimming not smooth.
Good	One or more of the following observed: Minor flickering at some point may exist. Dead travel may exist, which means there may be periods of time when the slider (or other form of control button) is moved without affecting the light level. These periods of dead travel are minor and most of the time not visible. Minor audible noise.
Best	Most of the following observed: No flickering, minimal audible noise (typically less than 25 dBA), wide dimming range - can dim down to 20% or less of light output.
High End (H.E.) Dead Travel	Determines how much, if any, dead travel exists at the top and bottom of the dimmer's range. Dead travel is when the slider can be moved without affecting the light level.
Low End (L.E.) Dead Travel	