



Dimmer Compatibility Guide

PLEASE NOTE: Compatibility list is based upon testing conducted by the manufacturer in a lab simulated environment. Actual results may vary.

Product Family Name: Filaments: Fully Compatible Dimming
Item Number: 776681
Ordering Code: LED4T9/27K/FIL/E26/2

Lamps per Dimmer

	Manufacturer	Product	Model Number	Overall Rating	Recommended		Notes
					Minimum	Maximum Tested*	
Incandescent/Halogen (Triac/Phase Cut/Leading Edge Dimmers)	Leviton	IllumaTech	IPI06	Good	1	6	Minor flicker at H.E. with 1, dims down to 15% with 1-6
		SureSlide	6633-P	Best	1	6	Dims down to 2% with 1-6
		Vizia	VPI06-1LZ	Good	2+	6	Minor flicker at L.E. with 3-6, dims down to 10% with 3-6
	Lutron	Toggler	TG-600	Best	1	6	Dims down to 10%
		Diva	DV-600	Best	1	6	Dims down to 1%
		Skylark	S-600	Best	1	6	Dims down to 1%
		Maestro	MAW-600	Good	1+	6	Minor flicker at L.E. with 3-6, dims down to 15% with 2-6
	Legrand	Titan	CD703-PW	Bad	1	6	Flicker at Medium with 1, flicker at L.E., Medium, H.E. with 2-3, dims down to 20% with 1-6
		Harmony	D703-PTC	Bad	1	6	Flicker at Medium with 1, flicker at L.E., Medium, H.E. with 2-3, dims down to 1% with 1-6
		Harmony	H703-PTC	Good	1	6	Flicker at Medium with 1-2, dims down to 1%
CFL/LED	Leviton	IllumaTech	IPL06	Best	1	6	Dims down to 5% with 1-6
		Sureslide	6674	Best	1	6	Dims down to 10% with 1-6
		Decora	6672	Best	1	6	Dims down to 10% with 1-6
	Lutron	Skylark	CTCL-153	Best	1	6	Dims down to 10% with 1-6
		Diva	DVCL-153PL	Best	1	6	Dims down to 10% with 1-6 without flicker, minor flicker after dims down to 10%
		Maestro	MACL-153MLH	Best	1	6	Dims down to 20% with 1-6 without flicker, minor flicker after dims down to 20% with 1-6
		Skylark	SCL-153P	Good	1	6	Dims down to 30% with 1-6 without flicker
		Toggler	TGCL-153PH	Best	1	6	Dims down to 1% with 1-6
		Radio RA	RA2RR-6CL-PD	Best	1	6	Dims down to 15% with 1-6, minor flicker after dims down to 10%
	Legrand	Harmony	DCL453-PTC	Best	1	6	Dims down to 15% with 1-6
Harmony		HCL453PTC	Best	1	6	Dims down to 15% with 1-6	
Electronic Low Voltage	Leviton	Vizia	VPE04	Good	1	6	Flicker at Medium with 1-6, dims down to 15%
		IllumaTech	IPE04	Good	1	6	Flicker at Medium with 1-6, dims down to 10%
		Decora	6615-P	Bad	1	6	Flicker at Medium and L.E. with 1-6, dims down to 40%
	Lutron	Skylark	SELVB-300P	Bad	1	6	Flicker at L.E. and Medium with 1, flicker at Medium with 2-6, flicker at H.E. with 5-6, dims down to 15%
		Skylark Countour	CTELV-303P	Good	1	6	Flicker at Medium with 1, flicker at Medium and H.E. with 2, flicker at Medium 1-6, dims down to 15%
		Diva	DVELV-300P	Good	1	6	Flicker at Medium with 1-6, dims down to 10%
		Maestro	MAELV-600	Good	1	6	Flicker at Medium with 1-6, dims down to 15%
		VIERTI	VTEL-600M-W	Best	1	6	Dims down to 15%
	Legrand	Scene Director	SCELV	Bad	1	6	Dims down to 30% with 1-6
	Magnetic Low Voltage	Leviton	Vizia	VPM-06	Good	3+	6
Decora			6613-P	Good	1	6	Flicker at Medium with 1-3, dims down to 10% with 1-6
Lutron		Maestro	MALV-600	Bad	5+	6	Dims down to 15%
		Harmony	DLV703-PW	Good	1	6	Flicker at H.E. with 2, dims down to 1%
Legrand		Titan	CDLV703-PW	Good	1	6	Flicker at H.E. with 3, dims down to 20%
Universal	Legrand	Adorne SofTap	ADTP703TU	Best	1	6	Dims down to 20% with 1-6
		Miro Decorator	DRD4-W	Not Compatible	1	6	Strobe at L.E. with 1-6
		Harmony	H703PTUTC	Bad	1	6	Dims down to 30%
		Adorne Whisper	ADWR700MMTUW2	Best	1	6	Dims down to 1% with 1-6
	Cooper	Adorne Touch	ADTH700MMTUM2	Best	1	6	Dims down to 1% with 1-6
		Decorator	DAL06P-C2-K-L	Good	1	6	Dims down to 20% with 1-6
		Skye	SAL06P-W-K-L	Good	1	6	Flicker below 15% with 1-6

*Maximum Tested (Lamps per Dimmer) - Additional lamps may work with your dimmer system. For maximum capacity please consult dimmer manufacturer.

†May experience "pop-on", lights cannot be turned on immediately to their minimum level. The slider needs to be raised above the minimum light level for the lights to first turn on if they were initially off. Then, the slider can be lowered to get to a lower light level; the dimmer cannot be turned on to just the minimum level.

Overall Rating	
Not Compatible	One or more of the following observed: Major flickering at various points, significant audible noise, no dimming range, does not turn off.
Bad	One or more of the following observed: Some flickering observed at various points, audible noise may be present, dimming not smooth.
Good	One or more of the following observed: Minor flickering at some point may exist. Dead travel may exist, which means there may be periods of time when the slider (or other form of control button) is moved without affecting the light level. These periods of dead travel are minor and most of the time not visible. Minor audible noise.
Best	Most of the following observed: No flickering, minimal audible noise (typically less than 25 dBA), wide dimming range - can dim down to 20% or less of light output.
High End (H.E.) Dead Travel	Determines how much, if any, dead travel exists at the top and bottom of the dimmer's range. Dead travel is when the slider can be moved without affecting the light level.
Low End (L.E.) Dead Travel	