

# LED SHOE BOX FIXTURE

## INSTALL INSTRUCTIONS

**PLEASE FIND A QUALIFIED ELECTRICIAN FOR INSTALLATION.** Please read the instructions before you install and use the luminaire.

### WARNING, CAUTIONS AND OPERATING INSTRUCTIONS

- To reduce the risk of death, personal injury or property damage from fire, electric shock, falling parts, cuts/abrasions, and other hazards read all warnings and instructions included with and on the fixture box and all fixture labels.
- Before installing, servicing, or performing routine maintenance upon this equipment, follow these general precautions.
- Commercial installation, service and maintenance of luminaires should be performed by a qualified licensed electrician.
- For The installation: If you are unsure about the installation or maintenance of the luminaires, consult a qualified licensed electrician and check your local electrical code.
- To prevent wiring damage or abrasion, do not expose wiring to edges of sheet metal or other sharp objects.
- Do not make or alter any open holes in an enclosure of wiring or electrical components during kit installation.
- Do not cover any part of the fixture; this can cause overheating.
- Do not use in areas that are not properly ventilated from strong fumes.

### WARNING: RISK OF FIRE OR ELECTRICAL SHOCK

- Turn off electrical power at fuse or circuit breaker box before wiring fixture to the power supply.
- Turn off the power when you perform any maintenance.
- Verify that supply voltage is correct by comparing it with the luminaire label information.
- Make all electrical and grounded connections in accordance with the National Electrical Code and any applicable local code requirements.
- All wiring connections should be capped with UL approved wire connectors.

### CAUTION: RISK OF INJURY


- Avoid direct eye exposure to the light source while it is on.
- Account for small parts and destroy packing material, as these may be hazardous to children.
- If wall mounting; the wall should be of sufficient strength to hold the fixture's weight.
- Suitable for Wet locations, IP65.

## INSTALLATION



### FIXED 4" SQUARE POLE MOUNT

1. Connect the lamp power input line with the main power cord.
2. Attach the mounting bracket to the pole, tighten the screws, the installation is completed.



### ADJUSTABLE SLIP FITTER (Item#: 83530)

1. The lamp pole diameter should be less than the connection tube diameter; loosen the screws on the connection tube.
2. Remove the 4" Square Pole Mount
3. Connect the lamp power input line with the main power cord.
4. Put the lamp pole into the connection tube, then tighten the screws, the installation is completed.
5. The lighting angle can be adjusted as required.



83530

