O+LIGHTING



MODEL SKU BR40 20W 1400LM 2700K E26 SE-350.027

DIMMER COMPATIBILITY LIST				
MANUFACTURER	BRAND	DIMMER MODEL	COMPATIBILITY	
		DVCL-153P	OK	
		DVELV-300P	OK	
	ļ l	DVELV-303P-AL	OK	
	DIVA	DVELC-303P-WH	OK	
		DV-600P-WH	OK	
		603P-WH	OK OK	
		DVWCL-153PH	OK OK	
		DVSCCL-153P	NC NC	
	SKYLARK	SELV-300P	OK OK	
		CTELV-303P	OK	
		S-600P	OK	
		CTCL-153P	NC	
		S-603P-WH	OK	
		SLV-600P	OK	
		S-600P-WH	OK	
		SCL-153P	NC	
		SCL-153P-WH	OK	
		SELV-300P-WH	OK	
		SLV-600-WH	NC NC	
	VIERTI	VTELV-600M	OK	
		NTLV-600-WH	OK OK	
	NOVA			
	LUMEA	LGCL-153PLH-WH	OK OK	
		LGCL-153P	OK	
		LGCL-153PL	OK	
LUTRON		MACL-153M	OK	
	MAESTRO	MAELV-600	OK	
		MACL-153M-WH	NC	
		MAELV-600-WH	OK	
	MAESTRO WIRELESS	MRF2-3LD	OK	
	TOGGLER	TG-600PR	NC	
	GRAFIK EYE OS	QSGRJ-6P	OK	
	INOVAT	NTELV-300	OK OK	
	INOVAI			
	RADIO RA2	RRD-6NA	OK NO	
		RRD-6CL	NC	
		RRD-6CL-WH	NC	
	-	1B3211	OK	
	-	1C13l1	OK	
	-	DVWCL-153PH/jsb1-85	OK	
	-	NTLV-600-WH/jsb1-88	OK	
	-	MRF2-3LDH	OK	
	_	DVELV-300P-WH	OK	
	VIVE	MRF2S-6CL-WH	NC	
		PD-6WCL-WH	NC	
	CASETA	PD-6WCL	NC NC	
	DIVA C*L	DVWCL-153PH-WH	OK	
	SPACER	SPSELV-600M	OK	
	NOVA T	NTELV-300-WH	OK.	
		NTLV-600-277-WH	NC	
	ARIADNI	AYCL-153P-WH	OK	
LEVITON	DECORA	R62-6674-P0W	OK	
	-	6674	OK	
	-	6161	OK	
	_	IPI06	OK	
	_	1PL06	OK	
		V47-C06579	OK OK	
	_	RTD01-10Z	OK OK	
	-	L20-6602	OK OK	
	-	6633-P	OK OK	
	-	52136	OK	
	-	RPI06-1/jsb1-103	OK	
	-	1PL06/jsb -92	OK	
		RTD01-10Z/jsb-100	OK	
	-			
	-	DMB01/6		
MAXXIMA	-	DMB01/6	OK	
MAXXIMA	-	DMB01/6 Maxxima DMA02	OK OK	
MAXXIMA FEIT	-	DMB01/6	OK	

DIMMER COMPATIBILITY

DIMINIER COMITATIBLE	
OK	Dims to < 15%
OK	Dims to 15 - 30%
NC.	Not Compatible

90+ LIGHTING NOTES

- 90+ LIGHTING ROTES

 1) This dimmer compatibility chart is provided by 90+ Lighting as a guidance for selecting a dimmer and lamp combination.
 2) The results may be different for each application depending on the installation conditions.
 3) 90+ Lighting reccomends to perform a previous test before the installation to verify the dimmer compatibility.
 4) We recommend using a 1/5 loading factor for incandescent dimmers when using with 90+ lamps.
 For example: a 400W dimmer should be loaded with a number of lamps whose combined power do not exceed 80W.

