

90+ LIGHTING



MODEL	ST19 7W 800LM 2700K E26
SKU	SE-RCL06.1107 -A

DIMMER COMPATIBILITY LIST				
MANUFACTURER	BRAND	DIMMER MODEL	COMPATIBILITY	
LUTRON	DIVA	DV-603P	OK	
		DVW-600PH-WH	NC	
		DV-603PH-WH	OK	
		DV-600PH-WH	OK	
		DVCL-153PH	NC	
		DVCL-153P-WH	OK	
		DVWCL-153PH-WHC	OK	
		DV-600P-WH	NC	
		DVCL-253PH	NC	
		DVCL-153P-WH	OK	
	DVELV-300P-WH	OK		
	DVWCL-153PH-WH	OK		
	-	DIVA C-L	DVWCL-153PH-WH	OK
	-	-	S-600	NC
	SKYLARK	-	CTCL-153P-WH	OK
		-	S-600PR-WH	OK
		-	S-603PGH-WH	NC
		-	S-600H-WH	NC
		-	S-10PH	NC
		-	SCL-153P-WH	NC
		-	S-600-IV	OK
		-	S-600-AL	OK
		-	S-603PH-WH	OK
		-	SCL-153PH-WH	OK
		-	S-603P-WH	OK
		-	SELV-300P-WH	OK
		-	SLV-600-WH	OK
		-	SPSELV-600M	OK
		-	D-600PH-DK	NC
	MAESTRO	-	MAW-600	NC
		-	MAW-600H-AL	NC
		-	MACL-153M-WH	NC
		-	MACL-153MR-WH	NC
		-	MACL-153MH-WH	NC
		-	MSCL-OP153MH-WH	NC
		-	TG-603PGH-WH	NC
		-	MAELV-600-WH	OK
		-	DV-603PR	OK
		-	D-600RH-DK	NC
	TOGGLER	-	TG-600PH-WH	OK
		-	TG-600PH-IV	NC
		-	TGCL-153PH-WH	OK
		-	D-600R-WH	OK
		-	D-600R-IV	NC
	ARIADNI	-	DVCL-153P-WH-3	OK
		-	AYCL-153P-WH	OK
		-	AY-600PH-WH	NC
		-	AYCL-153PH	OK
		-	CT-103P-WH	OK
		-	S-600P-WH	OK
-		TG-600PNLH-WH	OK	
-		LECL-153PH-WH	OK	
-		MACL-153MLRH-WH	OK	
-		MRF2S-6CL-WH	OK	
CASETA	-	PD-6WCL-WH	OK	
NOVA T	-	NTELV-300-WH	OK	
RADIO RA2	-	NTLV-600-277-WH	OK	
-	-	RRD-6CL-WH	OK	
LEVITON	-	6684	NC	
	-	NO.6683	NC	
	-	6631-LA	OK	
	-	IPI06	NC	
	-	S-600P-WH	OK	
	-	NO.6672	OK	
	-	603-6631-A	OK	
	-	6631-A	OK	
	-	NO.IPL06	NC	
	-	IPI10-1LZ	NC	
	-	6683-10Z	NC	
	-	IPI06-1LZ	OK	
	-	NO.6631	OK	
	-	6681	NC	
	DECORA	-	R62-6674-POW	OK
GE	-	18024	OK	
ALMOND	-	LUXDM600-12	OK	
AH	-	SDM3/1000	OK	
LEGRAND	-	SDM/600	NC	
-	-	HCL453PTC	NC	
COOPER	-	DAL06P-C2-K	NC	
	-	TAL06P-C2-K	NC	
	-	SAL06P-W-K	NC	
MAXXIMA	-	AAL06-C1	NC	
-	-	MEW-DM600	OK	
CTL	-	DM600-12-3/LED/WH	OK	
	-	DM600-12-3	OK	
ADORNE	-	ADPD453LW2	OK	
-	-	ADWR703HW4	OK	
EATON	-	TAL06P1-C5	OK	

DIMMER COMPATIBILITY	
OK	Dims to < 15%
OK	Dims to 15 - 30%
NC	Not Compatible

90+ LIGHTING NOTES

- 1) This dimmer compatibility chart is provided by 90+ Lighting as a guidance for selecting a dimmer and lamp combination.
- 2) The results may be different for each application depending on the installation conditions.
- 3) 90+ Lighting recommends to perform a previous test before the installation to verify the dimmer compatibility.
- 4) We recommend using a 1/5 loading factor for incandescent dimmers when using with 90+ lamps.

For example: a 400W dimmer should be loaded with a number of lamps whose combined power do not exceed 80W.