

# 90+ LIGHTING



MODEL	ST19 7W 600LM 2200K E26
SKU	SE-RCL06.1107-B

DIMMER COMPATIBILITY LIST					
MANUFACTURER	BRAND	DIMMER MODEL	COMPATIBILITY		
LUTRON	DIVA	DV-603P	OK		
		DVW-600PH-WH	NC		
		DV-603PH-WH	OK		
		DVCL-153PH	NC		
		DVCL-153P-WH	OK		
		DVWCL-153PH-WHC	OK		
		DV-600P-WH	NC		
		DVCL-253PH	NC		
		DVCL-153P-WH	OK		
		DVELV-300P-WH	OK		
		-	S-600	NC	
		-	D-600PH-DK	NC	
	-	DV-603PR	OK		
	-	S-600PR-WH	OK		
	SKYLARK	S-603PGH-WH	NC		
		S-10PH	NC		
		CTCL-153P-WH	OK		
		SCL-153P-WH	NC		
		S-600-IV	OK		
		S-600-AL	OK		
		S-603PH-WH	OK		
		S-600H-WH	NC		
		SCL-153PH-WH	OK		
		S-603P-WH	OK		
		SELV-300P-WH	OK		
		SLV-600-WH	OK		
		-	D-600RH-DK	NC	
		TOGGLER	TG-600PH-WH	OK	
			TG-600PH-IV	NC	
			TGCL-153PH-WH	OK	
			MAESTRO	MAW-600H-AL	NC
				MACL-153M-WH	NC
	MACL-153MR-WH			NC	
	MACL-153MH-WH	NC			
	MSCL-OP153MH-WH	NC			
	TG-603PGH-WH	NC			
	MAELV-600-WH	OK			
	MAW-600	NC			
	-	D-600R-WH	OK		
	-	D-600R-IV	NC		
	-	DVCL-153P-WH-3	OK		
	ARIADNI	AYCL-153P-WH	OK		
		AY-600PH-WH	NC		
		AYCL-153PH	OK		
		-	CT-103P-WH	OK	
		-	S-600P-WH	OK	
		-	TG-600PNLH-WH	OK	
		-	LECL-153PH-WH	OK	
		-	MACL-153MLRH-WH	OK	
		VIVE	MRF2S-6CL-WH	OK	
		CASETA	PD-6WCL-WH	OK	
	SPACER	SPSELV-600M	OK		
	NOVA T	NTELV-300-WH	OK		
	RADIO RA2	NTLV-600-277-WH	OK		
	-	RRD-6CL-WH	OK		
	LEVITON	-	6684	NC	
		-	NO.6683	NC	
		-	6631-LA	OK	
		-	IPI06	NC	
		-	S-600P-WH	OK	
-		NO.6672	OK		
-		603-6631-A	OK		
-		6631-A	OK		
-		NO.IPL06	NC		
-		IPI10-1LZ	NC		
-		6683-10Z	NC		
-		IPI06-1LZ	OK		
-		NO.6631	OK		
-		6681	NC		
DECORA		R62-6674-POW	OK		
GE		18024	OK		
ALMOND		LUXDM600-12	OK		
CTL		DM600-12-3	OK		
AH		SDM3/1000	OK		
LEGRAND		SDM/600	NC		
	HCL453PTC	NC			
COOPER	DAL06P-C2-K	NC			
	TAL06P-C2-K	NC			
	SAL06P-W-K	NC			
MAXXIMA	AAL06-C1	NC			
CTL	MEW-DM600	OK			
ADORNE	DM600-12-3/LED/WH	OK			
EATON	ADPD453LW2	OK			
	ADWR703HW4	OK			
	TAL06P1-C5	OK			

DIMMER COMPATIBILITY	
OK	Dims to < 15%
OK	Dims to 15 - 30%
NC	Not Compatible

## 90+ LIGHTING NOTES

- 1) This dimmer compatibility chart is provided by 90+ Lighting as a guidance for selecting a dimmer and lamp combination.
  - 2) The results may be different for each application depending on the installation conditions.
  - 3) 90+ Lighting recommends to perform a previous test before the installation to verify the dimmer compatibility.
  - 4) We recommend using a 1/5 loading factor for incandescent dimmers when using with 90+ lamps.
- For example: a 400W dimmer should be loaded with a number of lamps whose combined power do not exceed 80W.