


### Type-B I Ballast Bypass

#### Replaces 32W 4ft Fluorescent T8



#### Superior All-Around Light Distribution



#### FEATURES

- Bypass the Existing Ballast - Easy Direct-Wire Installation
- Full Glass Lens with 320° Light Distribution
- Uniform Light Output From End-to-End
- Universal Input Voltage - 120-277V
- 3-Year, 50,000 Hr Warranty
- Instant-ON with No Flicker
- UL Listed



Proprietary IC-Driver design allows for high efficiency and exceptional longterm performance



ARCHIPELAGO® Light Engine produces uniform light output from end-to-end




#### Specifications and Technical (ECO T8 I Type-B)


MODEL	BASE TYPE	WATTS / EQV.	LUMEN	CCT	LENGTH	VOLTAGE	CRI	PF	CARTON QTY	LIGHT DISTRIBUTION
LBP8F1641B	Bi-Pin G13	18W / 32W	1650LM	4100K	4FT	120-277V	83	>0.9	25	320°
LBP8F1750B	Bi-Pin G13	18W / 32W	1700LM	5000K	4FT	120-277V	83	>0.9	25	320°
LBP8F2241B	Bi-Pin G13	18W / 32W	2200LM	4100K	4FT	120-277V	83	>0.9	25	320°
LBP8F2350B	Bi-Pin G13	18W / 32W	2300LM	5000K	4FT	120-277V	83	>0.9	25	320°

- \* Not for use where exposed to the weather or moisture
- \*\* Suitable for use in totally enclosed fixtures
- \*\*\* Suitable for damp locations.

#### Installation Configuration



#### Light Distribution



**CAUTION: Single-ended input CANNOT be used with shunted lampholders**

Non-Shunted:



Shunted:



**WARNING** – To prevent wiring damage or abrasion, do not expose wiring to edges of sheet metal or other sharp objects.

**WARNING** – To avoid potential fire or shock hazard, do not use this retrofit kit in luminaires employing shunted bi-pin lamp holders. Note: Shunted lamp holders are found only in fluorescent luminaires with Instant-Start ballasts.

