











Dimmer Compatibility Chart on OVERDRIVE Dimmable LED lamps

No.	Dimmer Maker	IMAGE	Dimmer Type																	
				Overdrive Item #	686	643	633/634	631/632	647	620	637	640/722	639/642/648	610/602	605	607	669/670/699	658	691/692	695/696
				Overdrive Model #	L6G25DIM/30K	L4CDNDIM/E12/27K	L16HPAR38DIM /FL/30K/50K	L10HPAR30DIM/FL/30K/ L10HPAR30LNDIM/FL/30 K	L6MRGU10DI M/FL/30K	L8R30DIM/50K	L6HPAR20DIM/F L/30K	L6R200DIM /50K	L16R40DIM/50K/ L16R40DIM/30K	L10DL4DIM /30K	L10DL6DIM /30K	L12HDL6DIM/ 27K	L11NAOMDIM/27 K/L11NAOMDIM/5 0K	L5A19DIM/27K	L9A19DIM/27K	L15NAOMDIM/27K / L15NAOMDIM/50K
1-1	LEVITON	R62-6683-IW	forward phase(leading edge)	√	√	√	√	√	√	√	√	√	√	√	√	√	√			
1-2		C20-6681-IW	forward phase(leading edge)	√	√	√	√	√	√	√	√	√	√	√	√	√	√			
1-3		R01-RP106-1LI	forward phase(leading edge)	√	√	√	√	√	√	√	√	√	√	√	√	√	√			
1-4		6674-10W	forward phase(leading edge)	√	√	√	√	√	√	√	√	√	√	√	√	√	√			
1-5		R02-6615-POW	reverse phase(trailing edge)	√	×	√	√	×	√	×	√	√	√	√	√	√	√			
1-6		R15-JP106-1SE	forward phase(leading edge)	√	√	√	√	√	√	√	√	√	√	√	√	√	√			
1-7		1PE04-1LZ	reverse phase(trailing edge)	√	√	√	√	×	√	×	√	√	√	√	√	√	√			
1-8		R50-6602-IW	forward phase(leading edge)	√	√	√	√	√	√	√	√	√	√	√	√	√	√			
1-9		6633	forward phase(leading edge)	√	√	√	√	√	√	√	√	√	√	√	√	√	√			
1-10		IPL06	forward phase(leading edge)	√	√	√	√	√	√	√	√	√	√	√	√	√	√			
2-1	LUTRON	TTCL-100H-WH	forward phase(leading edge)	√	√	√	√	√	√	√	√	√	√	√	√	√	√			
2-2		D-600PH-DK	forward phase(leading edge)	×	√	√	√	√	×	√	√	×	×	×	√	√	√			
2-3		DVVL-600P-WH	forward phase(leading edge)	√	√	√	√	√	√	√	√	√	√	√	√	√	√			
2-4		NTLV-600-WH	forward phase(leading edge)	√	√	√	√	√	√	√	√	√	√	√	√	√	√			
2-5		DVELV-300P-WH	reverse phase(trailing edge)	√	√	√	√	√	√	√	√	√	√	√	√	√	√			
2-6		DV-603PG-WH	forward phase(leading edge)	√	√	√	√	√	√	√	√	√	√	√	√	√	√			
2-7		NLV-600-WH	forward phase(leading edge)	√	√	√	√	√	√	√	√	√	√	√	√	√	√			
2-8		CTCL-153PDH	forward phase(leading edge)	√	√	√	√	√	√	√	√	√	√	√	√	√	√			
2-9		D-603PH	forward phase(leading edge)	×	√	√	√	√	×	√	×	√	×	×	×	√	√			
2-10		TT-300NLN-WH	forward phase(leading edge)	√	√	√	√	√	√	√	√	√	√	√	√	√	√			
2-11		MRF2-3PD-1-1WH(Digital)	forward phase(leading edge)	√	√	√	√	√	√	√	√	√	√	√	√	√	√			
2-12		MA-600-WH(Digital)	forward phase(leading edge)	√	×	√	√	√	√	√	√	√	√	√	√	√	√			
2-13		MAW-600(Digital)	forward phase(leading edge)	√	√	√	√	√	√	√	√	√	√	√	√	√	√			
2-14		MRF2-6ND-120-WH(Digital)	forward phase(leading edge)	√	√	√	√	√	√	√	×	√	√	√	√	√	√			
2-15		RRD-10ND-WH(Digital)	forward phase(leading edge)	√	√	√	√	√	√	√	√	√	√	√	√	√	√			
2-16		VTLEV-600M-B-WH(Digital)	forward phase(leading edge)	√	√	√	√	√	√	√	√	√	√	√	√	√	√			
2-17		MAELV-600-WH(Digital)	reverse phase(trailing edge)	√	√	√	√	√	√	√	√	√	√	√	√	√	√			
2-18		MRF2-6ELV-120-WH(Digital)	reverse phase(trailing edge)	√	√	√	√	√	√	√	√	√	√	√	√	√	√			
2-19		AYCL-153P-WH	reverse phase(trailing edge)	√	√	√	√	√	√	√	√	√	√	√	√	√	√			
2-20		AYLV-600P-WH	forward phase(leading edge)	√	√	√	√	√	√	√	√	√	√	√	√	√	√			
2-21	TG-603PGH-WH	forward phase(leading edge)	√	√	√	√	√	√	√	√	√	√	√	√	√	√				
2-22	S-600PR-WH	forward phase(leading edge)	√	×	√	√	√	√	√	√	√	√	√	√	√	√				
2-23	CTCL-153P-WH	forward phase(leading edge)	√	√	√	√	√	√	√	√	√	√	√	√	√	√				
2-24	MACL-153M-WH (Digital)	forward phase(leading edge)	√	√	√	√	√	√	√	√	√	√	√	√	√	√				
2-25	DVCL-153P-WH	forward phase(leading edge)	√	√	√	√	√	√	√	√	√	√	√	√	√	√				
2-26	SCL-153PH-WH-C	forward phase(leading edge)	√	√	√	√	√	√	√	√	√	√	√	√	√	√				
2-27	LGCL-153PLH-WH-C	forward phase(leading edge)	√	√	√	√	√	√	√	√	√	√	√	√	√	√				
2-28	TGCL-153PH-WH-C	forward phase(leading edge)	√	√	√	√	√	√	√	√	√	√	√	√	√	√				
3-1	LEGRAND	DRD4-B(Digital)	forward phase(leading edge)	√	√	√	√	√	√	×	√	√	√	√	√	√	√			
4-1	PASS & SEYMOUR	CD703-PW	forward phase(leading edge)	×	√	√	√	×	×	×	√	√	√	√	√	√	√			
4-2		CDLV703-P	forward phase(leading edge)	×	√	√	√	×	×	×	√	√	√	√	√	√	√			
4-3		D703-PTC	forward phase(leading edge)	×	√	√	√	×	√	×	×	√	√	√	√	√	√			
4-4		DLV703-P	forward phase(leading edge)	×	√	√	√	×	×	×	×	√	√	√	√	√	√			