

## Dimmer Compatibility

Dimmer Detail						×=Flier, √=Good Compatibility				
NO.	Brand	Model No.	Load	Leading Edge	Trailing Edge	1 lamp	2 lamps	3 lamps	4 lamps	5 lamps
1	BILTEMA	30-300W	30-300W		▲	√	√	√	√	√
2	PHILIPS	SED-200A	200W		▲	√	√	√	√	√
3	Busch	6513 U-102	420W		▲	√	√	√	√	√
4	Schneider	SBD400RL	400W	▲		√	√	√	√	√
5	SIEMENS	5TG0200	500W	▲		√	√	√	√	√
6	Yankon	YY95111		▲		√	√	√	√	√
7	GIRA	0307 00/102	20-525W		▲	√	√	√	√	√
8	HPM	cat 250t	10-250W		▲	√	√	√	√	√
9	ELECTRIC	SSL510	400W	▲		×	×	√	√	√
10	TCL	A8051	400W	▲		×	√	√	√	√
11	Yankon	YV80501	300W	▲		√	√	√	√	√
12	WUYUN	W13-0162	20-300W		▲	√	√	√	√	√
13	anslut	400214	20-300W	▲		√	√	√	√	√
14	Schneider	315	315		▲	×	√	√	√	√
15	BILTEMA	46-913	20-300W		▲	√	√	√	√	√
16	GAMMA (TRADIN)	505811	5-150		▲	×	√	√	√	√
17	Legrand	9345	300W	▲		×	√	√	√	√
18	Schneider	SBD400	400W	▲		√	√	√	√	√
19	ELKO	315GLE	315W		▲	×	√	√	√	√
20	REV	136231	20-500W	▲		×	√	√	√	√
21	KOPP	8078	20-275W		▲	√	√	√	√	√
22	GIRA	2262 00	20-500W	▲		×	×	×	√	√
23	KOPP	8033	250W	▲		√	√	√	√	√
24	AURORA	DSP400X	60-400W	▲		√	√	√	√	√
25	Schneider	DSP400X	60-400W	▲		√	√	√	√	√
26	EVERFLOURISH	EF700DC	20-300W		▲	√	√	√	√	√
27	EVERFLOURISH	EFP700DC	20-300W		▲	√	√	√	√	√
28	KOPP	56356.01	400W	▲		√	√	√	√	√
29	REV Ritter	ET1 66012	25-500W		▲	√	√	√	√	√
30	CLIPSAL	32E450TM	450W		▲	√	√	√	√	√
31	CLIPSAL	32E450UDM	450W		▲	√	√	√	√	√
32	CLIPSAL	32E450LM	450W	▲		×	√	√	√	√
33	LUMEX	LT1D450LS	450W		▲	√	√	√	√	√
34	Legrand	CAT-400T	400W		▲	√	√	√	√	√
35	Legrand	CAT-400L	400W	▲		√	√	√	√	√
36	SAL	SDA 450	450W		▲	√	√	√	√	√
37	atom	AT9300/A	200W		▲	√	√	√	√	√
38	DIGINET	MEDM	2-400W		▲	√	√	√	√	√
39	HPM	200L	10-200W		▲	√	√	√	√	√
40	DETA	6021	70-400W		▲	√	√	√	√	√
41	CABAC	HNS610DT	350W		▲	√	√	√	√	√
42	TRADE SAVE	TSDM450W	450W		▲	√	√	√	√	√
43	CLIPSO	CLDM450	450W		▲	√	√	√	√	√
44	CLIPSAL	31E2PUDM	450W		▲	√	√	√	√	√
45	CLIPSAL	31E2RUDM	450W		▲	√	√	√	√	√
46	LUCCI	LD-KDT-200A	200W		▲	√	√	√	√	√