

## Safety Transformers

### PX Series

These safety transformers are specifically designed to supply 12-14 VAC and are suitable for direct connection to underwater pool/spa lights.

#### Applications

- LED pool lights • Submersible fixtures
- Outdoor landscape and decorative lighting

#### Features

- Mounting brackets on the top and bottom
- Built-in circuit protection disconnects power temporarily in case of overload\*
- Complies with NEC Code 680.23 requirements for underwater luminaries

Model #	Input Voltage	Output Voltage	Watts
<b>3R Beige Metal Enclosure</b>			
PX50	120 VAC, ½ A	12 or 13 VAC	50
PX100	120 VAC, 1 A	12 or 13 VAC	100
PX300	120 VAC, 3 A	12, 13 or 14 VAC	300
PX600	120 VAC, 6 A	12, 13 or 14 VAC	600
<b>3R Brown Stainless Steel Enclosure</b>			
PX50S	120 VAC, ½ A	12 or 13 VAC	50
PX100S	120 VAC, 1 A	12 or 13 VAC	100
PX300S	120 VAC, 3 A	12, 13 or 14 VAC	300
PX600S	120 VAC, 6 A	12, 13 or 14 VAC	600

\*Disconnection is not permanent; the transformer is equipped with a thermal protector. The circuit will "re-energize" when the transformer cools.



PX50



PX300S



Ratings PX50, 100, 300	
<b>Dimensions</b> H x W x D	7 ¼" x 5 ¼" x 4 ½" (184.2 mm x 133.4 mm x 114.3 mm)
<b>Knockout Dimensions</b>	
<b>Bottom</b>	(4) combination ½" - ¾"
<b>Left</b>	(2) combination ½" - ¾"
<b>Back</b>	(2) combination ½" - ¾"
<b>Right</b>	(2) combination ½" - ¾"
<b>Warranty</b>	1-year

Ratings PX600	
<b>Dimensions</b> H x W x D	10" x 10" x 5 ⅜" (254.0 mm x 254.0 mm x 136.5 mm)
<b>Knockout Dimensions</b>	
<b>Bottom</b>	(2) combination ½" - ¾", (4) combination ¾" - 1"
<b>Left</b>	(2) combination ½" - ¾"
<b>Back</b>	(2) combination ½" - ¾"
<b>Right</b>	(2) combination ½" - ¾"
<b>Warranty</b>	1-year