

# 90+ LIGHTING



MODEL	MR16 5W 40° 365lm 3000K GU5.3 12V COB DIMMABLE
SKU	SE-350.167

DIMMER COMPATIBILITY LIST									
MANUFACTURER	BRAND	DIMMER MODEL	TRANSFORMER	COMPATIBILITY					
				LIGHTTECH LET-60	HATCH RS12-60M	C-60	C-150	WACLIGHTING EN-1275-R-AR	MAGNETIC TRANSFORMER
LUTRON	VIVE	MRF2S-6CL-WH		NC	NC	-	-	-	OK
	CASETA	PD-6WCL-WH		OK	NC	-	-	-	OK
	DIVA	DV-600P-WH		OK	OK	-	-	-	OK
		DVELV-300P-WH		NC	NC	NC	NC	OK	OK
		DVLV-600P-WH		-	-	OK	OK	OK	-
	DIVA C+L	DVWCL-153PH-WH		OK	OK	-	-	-	OK
	MAESTRO	MACL-153M-WH		OK	NC	-	-	-	OK
		MAELV-600-WH		OK	NC	-	-	-	OK
	SKYLARK	S-603P-WH		OK	OK	-	-	-	OK
		SELV-300P-WH		OK	OK	-	-	-	OK
		SCL-153P-WH		OK	OK	-	-	-	OK
		SLV-600-WH		OK	NC	-	-	-	OK
	SPACER	SPSELV-600M		OK	OK	-	-	-	OK
	NOVA T	NTELV-300-WH		OK	NC	-	-	-	OK
		NTLV-600-277-WH		OK	OK	-	-	-	OK
	NOVA	NTLV-600-WH		-	-	OK	NC	OK	-
	RADIO RA2	RRD-6CL-WH		NC	NC	-	-	-	OK
	ARIADNI	AYCL-153P-WH		NC	NC	-	-	-	NC
TOGGLER	AYLV-600P-WH		-	-	OK	OK	OK	-	
		MRF2-3LD		-	-	OK	OK	OK	-
LEVITON	DECORA	R62-6674-P0W		OK	NC	-	-	-	-
LEGRAND	PASS & SEYMOUR	DLV703P		-	-	OK	OK	OK	-

#### DIMMER COMPATIBILITY

OK	Dims to < 15%
OK	Dims to 15 - 30%
NC	Not Compatible

#### 90+ LIGHTING NOTES

- 1) This dimmer compatibility chart is provided by 90+ Lighting as a guidance for selecting a dimmer and lamp combination.
- 2) The results may be different for each application depending on the installation conditions.
- 3) 90+ Lighting recommends to perform a previous test before the installation to verify the dimmer compatibility.
- 4) We recommend using a 1/5 loading factor for incandescent dimmers when using with 90+ lamps.  
For example: a 400W dimmer should be loaded with a number of lamps whose combined power do not exceed 80W.