

90+ LIGHTING



MODEL	G16.5 5W 350LM 3000K E12 Clear
SKU	SE-350.034

DIMMER COMPATIBILITY LIST				
MANUFACTURER	BRAND	DIMMER MODEL	COMPATIBILITY	
LUTRON	VIVE	MRF2S-6CL-WH	NC	
	CASETA	PD-6WCL-WH	NC	
	MAESTRO	MAELV-600	MAELV-600	OK
		MAELV-153M-WH	MAELV-153M-WH	NC
	SKYLARK	SELV-300P	SELV-300P	NC
		CTELV-303P	CTELV-303P	OK
		CTCL-153P	CTCL-153P	OK
		S-603P-WH	S-603P-WH	NC
		SLV-600P	SLV-600P	NC
		SCL-153P-WH	SCL-153P-WH	NC
		S-600P-WH	S-600P-WH	OK
	DIVA	DVELV-300P-WH	DVELV-300P-WH	OK
		DVELV-303P-AL	DVELV-303P-AL	OK
		DVELC-303P-WH	DVELC-303P-WH	OK
		DV-600P-WH	DV-600P-WH	NC
		603P-WH	603P-WH	OK
		DVCL-153P	DVCL-153P	OK
		DIVA C+L	DVWCL-153PH-WH	OK
	LUMEA	LGCL-153P	LGCL-153P	OK
		LGCL-153PL	LGCL-153PL	OK
		LGCL-153PLH-WH	LGCL-153PLH-WH	OK
	VIERTI	VTELV-600M	OK	
	NOVA	NTLV-600-WH	OK	
	SPACER	SPSELV-600M	OK	
	NOVA T	NTLV-300-WH	NTLV-300-WH	NC
		NTLV-600-277-WH	NTLV-600-277-WH	OK
		NTLV-600-WH/jsb1-88	NTLV-600-WH/jsb1-88	OK
	RADIO RA2	RRD-6CL-WH	RRD-6CL-WH	NC
		RRD-6NA	RRD-6NA	OK
	ARIADNI	AYCL-153P-WH	AYCL-153P-WH	OK
	-	1B3211	1B3211	OK
	-	1C1311	1C1311	OK
-	VTELV-600M	VTELV-600M	OK	
-	SLV-600P	SLV-600P	OK	
-	MRF2-3LDH	MRF2-3LDH	OK	
-	6674	6674	OK	
-	6161	6161	OK	
-	IPI06	IPI06	OK	
-	1PL06	1PL06	OK	
-	V47-C06579	V47-C06579	OK	
-	RTD01-10Z	RTD01-10Z	OK	
DECORA	R62-6674-P0W	R62-6674-P0W	OK	
	6674	6674	OK	
-	6633-P	6633-P	OK	
-	52136	52136	OK	
-	6161	6161	OK	
-	RPI06-1/jsb1-103	RPI06-1/jsb1-103	OK	
-	1PL06/jsb-92	1PL06/jsb-92	OK	
-	RTD01-10Z/jsb-100	RTD01-10Z/jsb-100	OK	
MAXXIMA	DMB01/6	DMB01/6	OK	
	DMA02	DMA02	OK	
FEIT	LGCL-153PLH-WH	LGCL-153PLH-WH	OK	
	LUTRO-S-600P-WH	LUTRO-S-600P-WH	OK	
	LEVITON-C20-06681-12A	LEVITON-C20-06681-12A	OK	

DIMMER COMPATIBILITY

OK	Dims to < 15%
OK	Dims to 15 - 30%
NC	Not Compatible

90+ LIGHTING NOTES

- 1) This dimmer compatibility chart is provided by 90+ Lighting as a guidance for selecting a dimmer and lamp combination.
 - 2) The results may be different for each application depending on the installation conditions.
 - 3) 90+ Lighting recommends to perform a previous test before the installation to verify the dimmer compatibility.
 - 4) We recommend using a 1/5 loading factor for incandescent dimmers when using with 90+ lamps.
- For example: a 400W dimmer should be loaded with a number of lamps whose combined power do not exceed 80W.