90+LIGHTING CANDLE 4.5W 320LM 3000K E26



| ODEL | CANDLE 4.5W 320LM 3000K | | |
|--------------|-------------------------|--------------------------------|---------------|
| (U | SE-350.152 | | |
| | DIMMER CO | MPATIBILITY LIST | |
| MANUFACTURER | BRAND | DIMMER MODEL | COMPATIBILITY |
| | | DVCL-153P | OK |
| | | DVELV-303P-AL | ОК |
| | DIVA | DVELC-303P-WH | OK |
| | | DV-600P-WH | NC |
| | | DVELV-300P-WH | OK |
| | DIV(A C) | 603P-WH | OK NC |
| | DIVA C*L | DVWCL-153PH-WH MACL-153M-WH | NC |
| | MAESTRO | MACL-153M-WH MAELV-600-WH | OK |
| | | CTELV-303P | OK |
| | | CTCL-153P | OK |
| | | S-603P-WH | NC |
| | | SLV-600P | ОК |
| | SKYLARK | SCL-153P-WH | NC |
| LUTRON | | S-600P-WH | ОК |
| | | SELV-300P-WH | NC |
| | | SLV-600-WH | NC |
| | | LGCL-153PL | ОК |
| | LUMEA | LGCL-153P | OK |
| | | LGCL-153PLH-WH | OK |
| | VIERTI | VTELV-600M | OK |
| | NOVA | NTLV-600-WH | OK |
| | | NTLV-600-WH/jsb1-88 | OK |
| | NOVA T | NTELV-300-WH | NC |
| | | NTLV-600-277-WH | NC |
| | RADIO RA2 | RRD-6NA | ОК |
| | | RRD-6CL-WH | NC |
| | VIVE | MRF2S-6CL-WH | NC |
| | CASETA | PD-6WCL-WH | NC |
| | SPACER | SPSELV-600M | NC |
| | ARIADNI | AYCL-153P-WH | NC |
| | - | 1B3211 | OK |
| | - | 1C13I1 | OK |
| | - | VTELV-600M | OK |
| | - | SLV-600P | OK |
| | - | MRF2-3LDH | OK |
| LEVITON | DECORA | R62-6674-POW | OK OK |
| | - | <u> </u> | OK |
| | | 6161 IPI06 | OK OK |
| | | 1PL06 | OK |
| | - | V47-C06579 | OK |
| | | RTD01-10Z | OK |
| | - | 6633-P | OK |
| | _ | 52136 | OK |
| | - | RPI06-1/jsb1-103 | OK |
| | - | 1PL06/jsb-92 | OK |
| | - | RTD01-10Z/jsb-100 | OK |
| MAXXIMA | - | DMB01/6 | OK |
| | - | DMA02 | ОК |
| FEIT | - | LGCL-153PLH-WH | OK |
| | - | LUTRO-S-600P-WH | OK |
| | - | LEVITON-C20-06681-12A | OK |

DIMMER COMPATIBILITY

| OK | Dims to < 15% |
|----|------------------|
| OK | Dims to 15 - 30% |
| NC | Not Compatible |
| | |

90+ LIGHTING NOTES

90+ Light ING NOTES
1) This dimmer compatibility chart is provided by 90+ Lighting as a guidance for selecting a dimmer and lamp combination.
2) The results may be different for each application depending on the installation conditions.
3) 90+ Lighting reccomends to perform a previous test before the installation to verify the dimmer compatibility.
4) We recommend using a 1/5 loading factor for incandescent dimmers when using with 90+ lamps.
For example: a 400W dimmer should be loaded with a number of lamps whose combined power do not exceed 80W.

