



WARNING

- For use on 120V AC, 60Hz circuits only.
- Do not overload the maximum wattage rating for any socket. The maximum rating for each socket is 20 watts.
- Do not overload the maximum wattage capacity in any run. The maximum rating for this product is 300 watts. The light string can be connected to additional, compatible light strings for a maximum of 960 watts for the entire run.

CAUTION

- Do not replace attachment plug. Contains a safety device (fuse) that should not be removed. Discard product if the attachment plug is damaged.
- This product employs overload protection (fuse). A blown fuse indicates an overload or short circuit situation. If the fuse blows, unplug the product from the outlet. Also unplug any additional strings or products that may be attached to the product. Replace the fuse as per the user servicing instructions (see below) and check the product. If the replacement fuse blows, a short-circuit may be present and the product should be discarded.
- Do not hardwire the light string.
- Keep lamps at least 16 feet from pools and spas.

NOTICE

- Periodically inspect the wires and sockets for degradation due to weather, UV light, or any other damage. Promptly replace the light string if any degradation or damage is observed.

Installation Instructions

- Suspend the light string by attaching a suspension cable (not included) to solid support structures, such as joists, beams or wall studs. Proper diameter cabling must be used for the maximum span distance between the supports.
- The light string can be supported from the suspension cable using zip ties or other appropriate support methods (support material not included).
- If a suspension cable is not used, the light string can be properly supported from solid structures using zip ties, eyebolts, or other appropriate support methods (support material not included).
- The maximum wattage for each candelabra socket is 20 Watts. Do not use lamps that exceed this wattage.

Light String Sets with Polarized Plugs

- The plug-in light string sets are supplied with an attached polarized plug that will only fit into a polarized outlet.
- If the plug does not fit into the outlet, reverse the plug and try again. If the plug still does not fit, contact a qualified electrician. Do not alter the plug.

Light String Sets with Overload Protection (Fuse) – Fuse Replacement Instructions

- Grasp the plug and remove it from the receptacle or other outlet device. Do not unplug by pulling on the cord.
- Open the fuse cover by sliding open the fuse access cover on top of the attachment plug towards the blades.
- Remove the fuse carefully by pushing the fuse from the other side.
- Replace the fuse only with an 8-amp, 120V fuse (provided with product).



25 FT. PATIO STRING LIGHTS SAFETY AND INSTALLATION INSTRUCTIONS

- Close the fuse cover by sliding the fuse access cover on top of the attachment plug.

⚠ WARNING

- Before installing, servicing, or performing routine maintenance upon this equipment, follow these general precautions.
- To reduce the risk of death, personal injury, or property damage from fire, electric shock, falling parts, cuts/abrasions, and other hazards, read all warnings and instructions included with and on the fixture box and all fixture labels.
- Proper grounding is required to ensure safety.
- Power must be turned off at the breaker before installation or maintenance.
- Installation, service, and maintenance of luminaires should be performed by a qualified licensed electrician.
- Wear gloves and eye protection at all times while installing, servicing, or performing maintenance on the luminaire, and avoid direct eye exposure to the light source while it is on.
- Do not install damaged product. Inspect luminaire for damage that may have occurred during transit. If damaged, contact the manufacturer immediately.
- These instructions do not purport to cover all details or variations in equipment nor to provide every possible contingency to meet in connection with installation, operation, or maintenance. Should further information be desired or should particular problems arise which are not covered sufficiently for the purchaser's or owner's purposes, contact the manufacturer.