

Titanium Series 3.0 MR16 7W High CRI #01-721-D



Magnetic Dimmer Switch Compatibility

Brand	Series	Model	Load	Dimmability (# of lamps)																								
				HA	ELCO CAN EL1499ICA EL1499S EL1499 EL1499R				NORA CAN NLR- 404/75/277V			JUL	ELG transf. BBC1ZA-B02XCI-2500X						ESBCO transf. 1105-12 (300W)									
				H1499ICAT H36LVRTAY H1499TAT H149RTAT								T I(x										
				1	2 3	4	1	2	3	4	5	1	2	3	1	2	1	2		3 4	4	5 (6	1	2	3	4	5
LUTRON	Diva	DVLV-600P	600	-												OK							Ī		Ī			
	Abella	ABLV-1000M	600		Х ОК		2	Х		OK		20-100% OK		Х	20-100%	Х			OK				35-100%				OK	
	Maestro	MALV-600	600	Х		Х			0	K	X		Х	OK		X					X							
		MALV-1000	1000	Х		Х			0	K	X 20-100%		Х	20-100%	25-100%		•	OK				Х				OK		
	Lyneo LX	LXLV-600PL	600	25-100%			15-100%					15-100%			25	15-100%					15-100%							
	Skylark	SLV-600P	600	25-100%			10-100%					15-100%			25	10-100%					10-100%							
	Toggler	TGLV-600PR	600	OK			OK					OK			OK		(OK	25-100%			25-100%						
LEVITON	Sure Slide	6613-PLA	600	25-100%			15-100%					15-100%			25	15-100%						30-100%						
	Vizia +	VPM10-1LZ	600	25-100%			20-100%					15-100%			25	25-100%						30-100%						
COOPER	Aspire	9536WS	1000	X																								

Table Key

OK= Fully compatible

___% = Compatible within this range, flicker outside the range

X= Incompatible

*GREEN CREATIVE has provided this dimmer switch compatibility chart for guidance when selecting a dimmer and lamp combination. Our lamps were tested for compatibility with the above listed dimmers. Dimmers that do not appear on the chart might still be compatible but have not been tested. All testing has been performed with a stable main supply. The quality of the local main, existing installation and wiring, as well as different manufacturer versions of the above dimmers and transformers may affect dimming performance. Since no assurance can be provided regarding these factors, it is a general recommendation to perform a test on-site prior to installing the LED lamps.



Titanium Series 3.0 MR16 7W High CRI #01-721-D

GREENCREATIVE

Electronic Dimmer Switch Compatibility



Table Key

OK= Fully compatible

___% = Compatible within this range, flicker outside the range

X= Incompatible

*GREEN CREATIVE has provided this dimmer switch compatibility chart for guidance when selecting a dimmer and lamp combination. Our lamps were tested for compatibility with the above listed dimmers. Dimmers that do not appear on the chart might still be compatible but have not been tested. All testing has been performed with a stable main supply. The quality of the local main, existing installation and wiring, as well as different manufacturer versions of the above dimmers and transformers may affect dimming performance. Since no assurance can be provided regarding these factors, it is a general recommendation to perform a test on-site prior to installing the LED lamps.