

SAMSUNG ELECTRONICS LED Lamp

Dimmable BR40 _15.5W

■ BR40 (90W Equivalent)



Product Code	Bar Code	Specification
SI-P8W181GF0US	887276988030	950lm / 15.5W / 60D / 2700K / E26
SI-P8W181GF1US	887276988047	975lm / 15.5W / 60D / 2700K / E26
SI-P8V181GF0US	887276987972	965lm / 15.5W / 60D / 3000K / E26
SI-P8V181GF1US	887276987989	990lm / 15.5W / 60D / 3000K / E26

Samsung LED Lamps are compatible with most forward phase dimmers and dimming systems. They are not compatible with reverse phase or ELV dimmers.

■ Dimmer Compatibility

Dimmer						Dimming Level @ 1 lamp (flux%)		Dimming Performance @ Multi-Lamps			
Manufacturer	Model	Power	Input	Frequency	Country/Region	Max	Min	2 Lamp	3 Lamp	4 Lamp	5 Lamp
LUTRON	TG-600P	600W	120V	60Hz	USA	100%	14%	Good	Good	Good	Good
LUTRON	TG-603PG	600W	120V	60Hz	USA	100%	20%	Good	Good	Good	Good
LUTRON	MIR-600	600W	120V	60Hz	USA	100%	7%	Good	Good	Good	Good
LUTRON	DV-603PG	600W	120V	60Hz	USA	100%	17%	Good	Good	Good	Good
LUTRON	MIR-600M-WH	600W	120V	60Hz	USA	100%	6%	Good	Good	Good	Good
LUTRON	S-600PH-WH	600W	120V	60Hz	USA	100%	10%	Good	Good	Good	Good
LEVITON	IP106	600W	120V	60Hz	USA	100%	14%	Good	Good	Good	Good
GE	6633-P	600W	120V	60Hz	USA	100%	16%	Good	Good	Good	Good
LEVITON	6683	600W	120V	60Hz	USA	100%	5%	Good	Good	Good	Good
LEVITON	700I	600W	120V	60Hz	USA	100%	5%	Good	Good	Good	Good
LEVITON	OG38L1	600W	120V	60Hz	USA	100%	6%	Good	Good	Good	Good
GE	18020	600W	120V	60Hz	USA	100%	13%	Good	Good	Good	Good
LUTRON	DV-600P-WH	600W	120V	60Hz	USA	100%	11%	Good	Good	Good	Good
LEVITON	6641	600W	120V	60Hz	USA	100%	5%	Good	Good	Good	Good
LEVITON	IPI10-1LZ	1000W	120V	60Hz	USA	100%	17%	Good	Good	Good	Good
LEVITON	6602	600W	120V	60Hz	USA	100%	5%	Good	Good	Good	Good
LEVITON	81500-W	1500W	120V	60Hz	USA	100%	10%	Good	Good	Good	Good
LEVITON	82000-W	2000W	120V	60Hz	USA	100%	11%	Good	Good	Good	Good
COOPER	9530W	600W	120V	60Hz	USA	100%	7%	Good	Good	Good	Good
COOPER	9532W	1000W	120V	60Hz	USA	100%	8%	Good	Good	Good	Good
GE	52129	600W	120V	60Hz	USA	100%	5%	Good	Good	Good	Good
GE	18025	1000W	120V	60Hz	USA	100%	11%	Good	Good	Good	Good
LUTRON	GL-600P-WH	600W	120V	60Hz	USA	100%	11%	Good	Good	Good	Good
LUTRON	DVCL-153P-WH	600W	120V	60Hz	USA	100%	22%	Good	Good	Good	Good
COOPER	RI061	600W	120V	60Hz	USA	100%	13%	Good	Good	Good	Good

Note 1. Dimming Performance : Good(Dimming Coverage without flicker : 75% ↑), Working(41~74%), Poor(40% ↓)