



Uphoria LED Downlight Retrofit Kit - Dimmer Compatibility List

Uphoria LED Downlight Kits may operate on other dimmers and dimming systems not listed below.

The existence of a dimmer on this list is not a guarantee or warranty of the compatibility of the kit / dimmer combination in all applications.

Actual performance of the products and dimmers may vary.

Dimmer Brand	Dimmer Model	4" DOWNLIGHT 1003923 8W				4" DOWNLIGHT 1003924 12W				5-6" DOWNLIGHT 1003925 12W				5-6" DOWNLIGHT 1003926 19W				5-6" DOWNLIGHT Eyeball 1003927 19W				5-6" DOWNLIGHT 1003922 23W			
		1 lamp	2 lamps	3 lamps	8 lamps	1 lamp	2 lamps	3 lamps	8 lamps	1 lamp	2 lamps	3 lamps	8 lamps	1 lamp	2 lamps	3 lamps	8 lamps	1 lamp	2 lamps	3 lamps	8 lamps	1 lamp	2 lamps	3 lamps	8 lamps
		Cooper	DLC038	Y	Y	Y	Y	Y	Y	Y	Y*	Y	Y	Y*	Y*	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y
Lutron	MA-600	N	N	N	N	N	N	N	N	N	N	N	N	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y*	Y*
Lutron	SCL-153PR	Y	Y	Y	N	Y	Y	Y	Y*	Y	Y	Y*	Y*	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y*	Y*
Lutron	MA CL-153-P	Y	Y	Y	N	Y	Y	Y	Y*	Y	Y	Y*	Y*	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y*	Y*
Leviton	6674	Y	Y	Y	Y	Y	Y	Y	Y*	Y	Y	Y*	Y*	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y*	Y*
Leviton	6673	Y	Y	Y	Y	Y	Y	Y	Y*	N	N	N	N	Y	Y	Y	Y	Y	Y	Y	N	N	N	N	N
Leviton	IPL06	Y	Y	Y	Y	Y	Y	Y	Y*	Y	Y	Y*	Y*	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y*	Y*
Leviton	IF3005	Y	Y	Y	Y	Y	Y	Y	Y*	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y
Lutron	CTCL-153P	Y	N	N	N	Y	Y	Y	Y*	Y	Y	Y	N	Y	Y	Y	Y*	Y	Y	Y	Y*	Y	Y	Y	N
Lutron	MRF2-6ND	N	N	N	N	Y	Y	Y	Y*	Y	Y	Y*	Y*	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y*	Y*
Lutron	DV CL-153P	Y	Y	Y	N	Y	Y	Y	Y*	Y	Y	Y*	Y*	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y*	Y*
Lutron	S-600P	Y	Y	Y	Y	Y	Y	Y	Y*	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y
Lutron	IPE04	Y	N	N	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y
Leviton	IPI06	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y*	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y*
Leviton	6615	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y
Leviton	6613	Y	Y	Y	Y	Y	Y	Y	Y*	Y	Y	Y	Y*	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y*

Y = Yes (Compatible)

N = No (Not Compatible)

* Depending on the application and the environment an audible noise may be heard with this Downlight Kit / Dimmer combination

Notes: Selector switch for 6674 is set to IN/LED. The slider on the DVCL is set in the middle.

USHIO is continually testing our LED products on various dimmers and dimming systems. We will continue to update this compatibility matrix as more results become available.

Specifications are subject to change without notice.