



**Uphoria LED Downlight Retrofit Kit - Dimmer Compatibility List**

Uphoria LED Downlight Kits may operate on other dimmers and dimming systems not listed below.

The existence of a dimmer on this list is not a guarantee or warranty of the compatibility of the kit / dimmer combination in all applications.

Actual performance of the products and dimmers may vary.

Dimmer Brand	Dimmer Model	4" DOWNLIGHT 1003923 8W				4" DOWNLIGHT 1003924 12W				5-6" DOWNLIGHT 1003925 12W				5-6" DOWNLIGHT 1003926 19W				5-6" DOWNLIGHT Eyeball 1003927 19W				5-6" DOWNLIGHT 1003922 23W			
		1 lamp	2 lamps	3 lamps	8 lamps	1 lamp	2 lamps	3 lamps	8 lamps	1 lamp	2 lamps	3 lamps	8 lamps	1 lamp	2 lamps	3 lamps	8 lamps	1 lamp	2 lamps	3 lamps	8 lamps	1 lamp	2 lamps	3 lamps	8 lamps
		Cooper	DLC038	Y	Y	Y	Y	Y	Y	Y	Y*	Y	Y	Y*	Y*	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y
Lutron	MA-600	N	N	N	N	N	N	N	N	N	N	N	N	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y*	Y*
Lutron	SCL-153PR	Y	Y	Y	N	Y	Y	Y	Y*	Y	Y	Y*	Y*	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y*	Y*
Lutron	MA CL-153-P	Y	Y	Y	N	Y	Y	Y	Y*	Y	Y	Y*	Y*	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y*	Y*
Leviton	6674	Y	Y	Y	Y	Y	Y	Y	Y*	Y	Y	Y*	Y*	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y*	Y*
Leviton	6673	Y	Y	Y	Y	Y	Y	Y	Y*	N	N	N	N	Y	Y	Y	Y	Y	Y	Y	N	N	N	N	N
Leviton	IPL06	Y	Y	Y	Y	Y	Y	Y	Y*	Y	Y	Y*	Y*	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y*	Y*
Leviton	IF3005	Y	Y	Y	Y	Y	Y	Y	Y*	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y
Lutron	CTCL-153P	Y	N	N	N	Y	Y	Y	Y*	Y	Y	Y	N	Y	Y	Y	Y*	Y	Y	Y	Y*	Y	Y	Y	N
Lutron	MRF2-6ND	N	N	N	N	Y	Y	Y	Y*	Y	Y	Y*	Y*	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y*	Y*
Lutron	DV CL-153P	Y	Y	Y	N	Y	Y	Y	Y*	Y	Y	Y*	Y*	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y*	Y*
Lutron	S-600P	Y	Y	Y	Y	Y	Y	Y	Y*	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y
Lutron	IPE04	Y	N	N	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y
Leviton	IPI06	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y*	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y*
Leviton	6615	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y
Leviton	6613	Y	Y	Y	Y	Y	Y	Y	Y*	Y	Y	Y	Y*	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y*

Y = Yes (Compatible)

N = No (Not Compatible)

\* Depending on the application and the environment an audible noise may be heard with this Downlight Kit / Dimmer combination

Notes: Selector switch for 6674 is set to IN/LED. The slider on the DVCL is set in the middle.

**USHIO is continually testing our LED products on various dimmers and dimming systems. We will continue to update this compatibility matrix as more results become available.**

Specifications are subject to change without notice.