

2/3/2016				R20	R20	R20 SE	R20	R20	R20	R20 SE	R20	R20 SE	BR30	BR30	BR30	BR30
				73780, 73781, 73801	78489, 78490	79656, 79659, 79653	78694, 78695, 78696	78485, 78486, 79120	79172, 79173, 79174	79637, 79638	78016, 78017	78390	78691, 78692, 78693	78487, 78488, 78703	73775, 73776, 73777, 73778, 73779	79169, 79170, 79171
Brands	Series	Model	Type*	5W	6W	7W	7W	7W	7W	7W	8W	8W	9W	9W	9W	9W
Lutron	Ariadni	AYCL-153P	L		✓ 1-25			✓ 1-21		✓ 1-21		✓ 1-18	✓ 1-16			
Lutron	Diva	250W CL Dimmers	L													
Lutron	Skylark	CTCL-153P	L		✓ 1-25			✓ 1-21		✓ 1-21		✓ 1-18	✓ 1-16			
Lutron	Diva	DVCL-153P	L		✓ 1-25			✓ 1-21		✓ 1-21		✓ 1-18	✓ 1-16			
Lutron	Panel Module	GP (Harrier) Card	L	✓ 1-44		✓ 1-63					✓ 1-60	✓ 1-57				
Lutron	Grafik Eye 3000	Grafik Eye 3000 Family	L	✓ 1-62								✓ 1-24				✓ 1-44
Lutron	Grafik QS	Grafik Eye QS	L	✓ 1-62	✓ 1-17				✓ 1-50			✓ 1-24			✓ 1-48	✓ 1-44
Lutron	Grafik T	GT-150	L													
Lutron	Grafik T	GTJ-150	L													
Lutron	HomeWorks QS	HQRD-10ND	L		✓ 1-22	✓ 1-21	✓ 1-30	✓ 1-20			✓ 1-18	✓ 1-18	✓ 1-16		✓ 1-16	✓ 1-16
Lutron	HomeWorks QS	HQRD-6NA	T		✓ 1-13	✓ 1-21		✓ 1-21		✓ 1-21	✓ 1-18	✓ 1-18	✓ 1-16	✓ 1-16	✓ 1-16	✓ 1-16
Lutron	HomeWorks QS	HQRD-6ND	L		✓ 1-13						✓ 1-18	✓ 1-18				
Lutron	HomeWorks QS	HQRD-6CL (H2)/ HQRA-6CL (H2)	L													
Lutron	HomeWorks QS	HQRD-H6BRL	L													
Lutron	Panel Module	HW/LP-RPM-4A-120	T	✓ 1-81	✓ 1-26	✓ 1-164	✓ 1-125	✓ 1-65	✓ 1-60			✓ 1-36	✓ 1-75	✓ 1-49	✓ 1-57	✓ 1-50
Lutron	Panel Module	HW/LP-RPM-4U-120	L		✓ 1-42			✓ 1-111				✓ 1-57				
Lutron	HomeWorks QS	HxD-6ND	L	✓ 1-13			✓ 1-21	✓ 1-12	✓ 1-11		✓ 1-19	✓ 1-18				
Leviton	IllumaTech	IPE04-1LZ	T													
Lutron	HomeWorks QS	LQSE-4A1-D/ MQSE-4A1-D/ MQSE-3A1/ MQSE-2A1-D	T			✓ 1-16			✓ 1-13							
Lutron	Maestro RF	MRF2-6ELV	T			✓ 1-21		✓ 1-21		✓ 1-21			✓ 1-16	✓ 1-16	✓ 1-16	✓ 1-16
Lutron	Maestro	MACL-153M	L			✓ 1-21						✓ 1-18				
Lutron	Maestro RF	MRF2-6ND	L		✓ 1-13						✓ 1-18	✓ 1-18				
Lutron	Maestro wireless	MRF2-6CL	L													
Lutron	Maestro Sensor	MSCL-OP153M (T2) MSCL-VP153M (T2)	L			✓ 1-21		✓ 1-21		✓ 1-21		✓ 1-18	✓ 1-16			✓ 1-16
Lutron	Nova	NLV600	L													
Lutron	Nova T	NTCL-250	L													
Lutron	Caseta Wireless	PD-6WCL	L			✓ 1-21				✓ 2-21						
Lutron	Grafik Eye	PHPM-PA	T	✓ 1-81		✓ 1-191		✓ 1-65	✓ 1-60	✓ 1-65				✓ 1-49	✓ 1-57	✓ 1-50
Lutron	Grafik Eye	PHPM-WBX	T	✓ 1-81		✓ 1-191		✓ 1-65	✓ 1-60	✓ 1-65				✓ 1-49	✓ 1-57	✓ 1-50
Lutron	RadioRA 2	RRD-10ND	L		✓ 1-22	✓ 1-21	✓ 1-30	✓ 1-20			✓ 1-18	✓ 1-18	✓ 1-16		✓ 1-16	✓ 1-16
Lutron	RadioRA 2	RRD-6D	L													
Lutron	RadioRA 2	RRD-6CL	L													
Lutron	RadioRA 2	RRD-6NA	T		✓ 1-13	✓ 1-21		✓ 1-20		✓ 1-21	✓ 1-18	✓ 1-18	✓ 1-16	✓ 1-16		✓ 1-16
Lutron	RadioRA 2	RRD-H6BRL	L													
Lutron	Stanza	SZ-6ND	L	✓ 1-13			✓ 1-21	✓ 1-12	✓ 1-11		✓ 1-19	✓ 1-18				
Lutron	Toggle	TGCL-153P	L		✓ 1-25			✓ 1-21		✓ 1-21		✓ 1-18	✓ 1-16			

*Type: L: Leading Edge, T: Trailing Edge

Note: The first number after a check mark is a minimum number of lamps per dimmer; the second number after a check mark is a maximum number of lamps per dimmer.

BR30 Contractor	BR30 SE	BR30	BR30 SE	BR30	BR30	BR30	BR30 SE	BR40 SE	BR40	BR40 SE	BR40 SE	BR40	BR40
73954, 73957, 73956	79657, 79660, 79654	78413, 78415, 79121	79640, 79639	79167, 79166, 79168, 79178	78917, 78918	78014, 78015, 78018, 72568	78388	78389, 72889	78416, 78484, 79122	79658, 79661, 79655	79641, 79642	79175, 79176, 79177	78386
9W	11W	11W	11W	11W	12W	12W	12W	12W	15W	15W	15W	15W	16W
	✓ 1-13				✓ 1-12	✓ 1-12	✓ 1-11		✓ 1-10		✓ 1-10		✓ 1-9
	✓ 1-22									✓ 1-16			
	✓ 1-13				✓ 1-12	✓ 1-12	✓ 1-11		✓ 1-10	✓ 1-10	✓ 1-10		✓ 1-9
	✓ 1-13				✓ 1-12	✓ 1-12	✓ 1-11		✓ 1-10	✓ 1-10	✓ 1-10		✓ 1-9
	✓ 1-40	✓ 1-27	✓ 1-28		✓ 1-47	✓ 1-68	✓ 1-67	✓ 1-49	✓ 1-22		✓ 1-23	✓ 1-19	✓ 1-59
	✓ 1-40			✓ 1-47		✓ 1-28	✓ 1-28	✓ 1-66				✓ 1-27	✓ 1-24
	✓ 1-40			✓ 1-47	✓ 1-19	✓ 1-28	✓ 1-28	✓ 1-66				✓ 1-27	✓ 1-24
	✓ 1-13									✓ 1-10			
	✓ 1-13									✓ 1-10			
✓ 1-16	✓ 1-8	✓ 1-13		✓ 1-13	✓ 1-12	✓ 1-12	✓ 1-11	✓ 1-12				✓ 1-9	✓ 1-9
	✓ 1-13	✓ 1-13	✓ 1-13	✓ 1-13	✓ 1-12	✓ 1-12	✓ 1-11	✓ 1-12				✓ 1-10	✓ 1-9
	✓ 1-8				✓ 1-12	✓ 1-12	✓ 1-11	✓ 1-12					✓ 1-9
	✓ 1-13							✓ 1-12		✓ 1-10		✓ 1-10	
	✓ 1-9									✓ 1-6			
✓ 1-133	✓ 1-48		✓ 1-52	✓ 1-47	✓ 1-29	✓ 1-42	✓ 1-42	✓ 1-97	✓ 1-37	✓ 1-37	✓ 1-41	✓ 1-32	✓ 1-37
					✓ 1-47	✓ 1-68		✓ 1-138					✓ 1-59
	✓ 1-8	✓ 1-18	✓ 1-8		✓ 1-14	✓ 1-21	✓ 1-21	✓ 1-15	✓ 1-6	✓ 1-7	✓ 1-7	✓ 1-5	✓ 1-18
✓ 1-13	✓ 1-9									✓ 1-7			
	✓ 1-13	✓ 1-13	✓ 1-13	✓ 1-13				✓ 1-12		✓ 1-10		✓ 1-10	
	✓ 1-13	✓ 1-13				✓ 1-12			✓ 1-10	✓ 1-10	✓ 1-10		✓ 1-9
	✓ 1-8				✓ 1-12	✓ 1-12		✓ 1-12					✓ 1-9
	✓ 1-13							✓ 1-12		✓ 1-10		✓ 1-10	
	✓ 1-13	✓ 1-13				✓ 1-12			✓ 1-10	✓ 1-10	✓ 1-10		✓ 1-9
	✓ 1-22									✓ 1-16			
	✓ 1-13	✓ 1-13	✓ 1-13							✓ 1-10			
✓ 1-135	✓ 1-48	✓ 1-51	✓ 1-52	✓ 1-47				✓ 1-99	✓ 1-37	✓ 1-37	✓ 1-41	✓ 1-32	
✓ 1-135	✓ 1-48	✓ 1-51	✓ 1-52	✓ 1-47				✓ 1-99	✓ 1-37	✓ 1-37	✓ 1-41	✓ 1-32	
✓ 1-16	✓ 1-13	✓ 1-13		✓ 1-13	✓ 1-12	✓ 1-12	✓ 1-11	✓ 1-12		✓ 1-10		✓ 1-9	✓ 1-9
								✓ 1-12					
	✓ 1-13							✓ 1-12		✓ 1-10		✓ 1-10	
	✓ 1-13	✓ 1-13	✓ 1-13	✓ 1-13	✓ 1-12	✓ 1-12		✓ 1-12		✓ 1-10		✓ 1-10	✓ 1-9
	✓ 1-9									✓ 1-6			
	✓ 1-8	✓ 1-8	✓ 1-8		✓ 1-14	✓ 1-21	✓ 1-21	✓ 1-15	✓ 1-6	✓ 1-7	✓ 1-7	✓ 1-5	✓ 1-9
	✓ 1-13				✓ 1-12	✓ 1-12	✓ 1-11		✓ 1-10	✓ 1-10	✓ 1-10		✓ 1-9

Please Note:
• The recommended list is based upon testing conducted by the manufacturer in a lab simulated environment, and the results can vary in certain field applications due to a number of factors.
• The absence of a dimmer from this chart does not necessarily imply incompatibility.
• Please reference the dimmer manufacturer's instructions for installation.

Application Notes

- In situations where there are multiple dimming circuits sharing the same breaker feed, ELV dimmers should be used
- For best dimming results, the ELV dimmer or trailing edge dimmer type is recommended.
- ELV dimmer or trailing edge type dimmer required the neutral wire for installation.

SYLVANIA is a registered trademark of OSRAM SYLVANIA Inc.

SEE THE WORLD IN A NEW LIGHT is a registered trademark of OSRAM SYLVANIA Inc.

Product specifications subject to change.

All other trademarks are those of their respective owners.