

# 90+ LIGHTING



MODEL	BR30 11W 800LM 2700K E26
SKU	SE-RCU02.1111 - B

DIMMER COMPATIBILITY LIST			
MANUFACTURER	BRAND	DIMMER MODEL	COMPATIBILITY
LUTRON	DIVA	DV-603P	NC
		DVWCL-153PH-WH	NC
		DVW-600PH-WH	NC
		DV-603PH-WH	NC
		DV-600PH-WH	NC
		DVCL-153PH	NC
		DVCL-153P-WH	OK
		DVWCL-153PH-WHC	OK
		DVCL-253PH	NC
		DVELV-300P-WH	OK
	-	S-600	NC
	-	D-600PH-DK	NC
	MAESTRO	MAW-600	NC
		MAW-600H-AL	NC
		MACL-153M-WH	NC
		MACL-153MR-WH	NC
		MACL-153MH-WH	NC
		MSCL-OP153MH-WH	NC
		MACL-153MLH-WH	NC
		TG-603PGH-WH	NC
		MAELV-600-WH	OK
		-	DV-603PR
	SKYLARK	S-600PR-WH	NC
		S-603PGH-WH	NC
		S-600H-WH	NC
		S-10PH	NC
		CTCL-153P-WH	OK
		SCL-153P-WH	NC
		S-600-IV	NC
		S-600-AL	NC
		S-603PH-WH	OK
		S-600P-WH	NC
		SCL-153PH-WH	OK
		SELV-300P-WH	OK
		SLV-600-WH	OK
		S-603P-WH	OK
		-	D-600RH-DK
	TOGGLER	TG-600PH-WH	NC
		TG-600PH-IV	NC
		TGCL-153PH-WH	OK
	-	D-600R-WH	NC
	-	D-600R-IV	NC
	ARIADNI	AYCL-153P-WH	OK
		AY-600PH-WH	NC
		AYCL-153PH	OK
	VIVE	MRF2S-6CL-WH	NC
	CASETA	PD-6WCL-WH	OK
	SPACER	SPSELV-600M	OK
	NOVA T	NTELV-300-WH	OK
		NTLV-600-277-WH	OK
RADIO RA2	RRD-6CL-WH	NC	
DECORA	R62-6674-P0W	OK	
	-	6684	NC
	-	NO.6683	OK
	-	6631-LA	OK
	-	IPI06	NC
	-	S-600P-WH	NC
	-	NO.6672	OK
	-	603-6631-A	OK
	-	6631-A	OK
	-	NO.IPL06	OK
	-	IPI10-1LZ	OK
	-	6683-10Z	OK
	-	IPI06-1LZ	OK
	-	NO.6631	OK
	-	6681	NC
GE	18024	OK	
ALMOND	-	LUXDM600-12	OK
CTL	-	DM600-12-3	OK
AH	-	SDM3/1000	OK
	-	SDM/600	OK
LEGRAND	-	HCL453PTC	NC
COOPER	-	DAL06P-C2-K	NC
	-	TAL06P-C2-K	NC
	-	SAL06P-W-K	NC
	-	AAL06-C1	NC
MAXXIMA	-	MEW-DM600	OK

DIMMER COMPATIBILITY	
OK	Dims to < 15%
OK	Dims to 15 - 30%
NC	Not Compatible

### 90+ LIGHTING NOTES

- 1) This dimmer compatibility chart is provided by 90+ Lighting as a guidance for selecting a dimmer and lamp combination.
- 2) The results may be different for each application depending on the installation conditions.
- 3) 90+ Lighting recommends to perform a previous test before the installation to verify the dimmer compatibility.
- 4) We recommend using a 1/5 loading factor for incandescent dimmers when using with 90+ lamps.  
For example: a 400W dimmer should be loaded with a number of lamps whose combined power do not exceed 80W.