


## Hippo Strip to Wire Tape Light Connectors Instructions

1. Lift up the clear plastic tabs and slide your 10-millimeter wide RGB LED strip into the connector on the clasp side as far as you can, making sure it is on top of the grooves.
2. Press the tab down tightly. The sharp grooves should pierce up through the bottom of the strip and through the copper pads, making a solid connection.
3. The four 20-gauge RGB wires are already connected on other side of the clasp. Separate and connect each wire from the Hippo connector into RGB controller wire terminal. You may need to use wire stripper to remove a millimeter of the colored insulation to ensure a better connection to the terminal.



4. Check to make sure the installation is complete and secure.

There's no need to peel off the nano parylene coating on waterproof strips. However, the tape light does not maintain its waterproof IP65 rating after cutting and reconnecting the strips.