



Square Downlights Dimmer Compatibility

ProLED Product Code & Product Number

QDL4FR10/927/LED (99952)	QDL4FR10/940/LED (99954)
QDL4FR10/930/LED (99953)	QDL4FR10/950/LED (99955)
QDL6FR15/927/LED (99956)	QDL6FR15/940/LED (99958)
QDL6FR15/930/LED (99957)	QDL6FR15/950/LED (99959)

Lamps per 600W Dimmer

	Wattage	Inrush	# of Lamps
	10	55W	10
	15	66W	9

Brand	Model	Load	Type	Compatibility	Max Units	Compatibility	Max Units
Lutron®	MACL-153M-WH	600W	INC	Yes	9	Yes	10
	S-600PR-WH	600W	INC	Yes	9	Yes	10
	SPSLV-600-WH	600W	INC	Yes	9	Yes	10
	DVLV-603P-IV	600W	INC	Yes	9	Yes	10
	MALV-600-IV	600W	INC	Yes	9	Yes	10
	DVW-603PGH-WH	600W	INC	Yes	9	Yes	10
	MIR-600THW-WH	600W	INC	Yes	9	Yes	10
	CTCL-153P	150W	INC	Yes	10	Yes	15
	SLV-600P-WH	600W	INC	Yes	9	Yes	10
	DVW-603P6H-WH	600W	INC	Yes	9	No	10
	CT-603PG	600W	INC	Yes	9	Yes	10
	NT-1000	1000W	INC	Yes	15	Yes	18
	S-603P	600W	INC	Yes	9	Yes	10
	DV-600P	600W	INC	Yes	9	Yes	10
	DVCL-153P-WH	150W	INC	Yes	10	Yes	15
Leviton®	IPL06	600W	INC	Yes	9	Yes	10
	6672	600W	INC	Yes	9	Yes	10
	6631	600W	INC	Yes	9	Yes	10
	6674	600W	INC	Yes	9	Yes	10
	1A23O5	600W	INC	Yes	9	Yes	10
	0B33K1	600W	INC	Yes	9	Yes	10

*Dimmers specifically designed for use with CFL or LED lamps neutralize the initial "Inrush Current" of each lamp. Other types of dimmers must take Inrush Current into account when calculating maximum # of lamps allowed for each dimmer.