+LIGHTING



MODEL A21 14W 1100LM 3000K E26 SKU SE-350.052

DIMMER COMPATIBILITY LIST				
MANUFACTURER	BRAND	DIMMER MODEL	COMPATIBILITY	
	<u> </u>	DVCL-153P	OK	
		DVELV-300P	OK	
	DIVA	DVELV-303P-AL	OK OK	
		DVELC-303P-WH DV-600P-WH	OK OK	
		DV-600P-WH	OK OK	
		603P-WH	OK OK	
		DVWCL-153PH	OK OK	
		DVSCCL-153P	NC NC	
		SELV-300P	OK	
	SKYLARK	CTELV-303P	OK	
		S-600P	OK	
		CTCL-153P	OK	
		S-603P-WH	OK	
		SLV-600P	OK	
		SELV-300P-WH	OK	
		SLV-600-WH	OK	
		S-600P-WH	OK	
		CTCL-153P	OK	
	-	1B3211	OK	
	-	1C13l1	OK	
	VIVE	MRF2S-6CL-WH	NC	
	DIVA C*L	DVWCL-153PH-WH	OK	
		MAELV-600-WH	OK	
LUTRON	MAESTRO	MAELV-600	OK	
LUTRUN		MACL-153M	NC	
	SPACER	SPSELV-600M	OK	
	NOVA T	NTELV-300-WH	OK	
	_	NTLV-600-277-WH	OK	
	ARIADNI	AYCL-153P-WH	OK	
	VIERTI	VTELV-600M	OK	
	-	DVWCL-153PH/jsb1-85	OK	
	-	NTLV-600-WH/jsb1-88	OK	
	NOVA	NTLV-600-WH	OK OK	
	LUMEA	LGCL-153PLH-WH	OK	
		LGCL-153PL	OK NG	
	MATCTDO MUDELECC	LGCL-153P	NC NC	
	MAESTRO WIRELESS	MRF2-3LD RRD-6CL	OK NC	
	RADIO RA2	RRD-6CL-WH	NC NC	
	RADIO RA3	RRD-6NA	OK	
	TOGGLER	TG-600PR	NC	
	GRAFIK EYE QS	OSGRJ-6P	OK	
	INOVAT	NTELV-300	OK OK	
		PD-6WCL	NC NC	
	CASETA	PD-6WCL-WH	NC NC	
	-	MRF2-3LDH	OK	
	-	MACL-153M-WH	OK	
	-	SCL-153P-WH	NC	
	-	DVELV-300P-WH	OK	
LEVITON	-	RPI06-1/jsb1-103	OK	
	-	1PL06/jsb-92	OK	
	-	RTD01-10Z/jsb-100	OK	
	-	IPI06	OK	
	-	1PL06	OK	
	-	RTD01-10Z	OK	
	-	6674	OK	
	-	6633-P	OK	
	-	52136	OK	
	DECORA	R62-6674-P0W	OK	
	-	V47-C06579	OK	
	-	6161	OK	
	-	L20-6602	NC	
FEIT	-	LGCL-153PLH-WH	OK	
	-	LUTRO-S-600P-WH	OK	
FEIT				
FEIT	-	LEVITON-C20-06681-12A	OK	
FEIT MAXXIMA				

DIMMER COMPATIBILITY

OK	Dims to < 15%
OK	Dims to 15 - 30%
NC	Not Compatible

90+ LIGHTING NOTES

- 1) This dimmer compatibility chart is provided by 90+ Lighting as a guidance for selecting a dimmer and lamp combination.

- The results may be different for each application depending on the installation conditions.
 90+ Lighting reccomends to perform a previous test before the installation to verify the dimmer compatibility.
 We recommend using a 1/5 loading factor for incandescent dimmers when using with 90+ lamps.
 For example: a 400W dimmer should be loaded with a number of lamps whose combined power do not exceed 80W.

