

Dimmer Compatibility for 120V Wafers

****MVOLT wafers are compatible with any 0-10V dimmer****

Static & Switchable White Wafers

WF3, WF4, WF6, WF8

Leviton	Lutron		Sensorswitch	Synergy/Leviton
6633-PA	Maestro MACL-153M (TX)	Maestro MACL-LFQ	nSP5 PCD 2W	ISD 600 I 120/IPI06
IPL06-LED/INC mode	Maestro Wireless MRF2-6ELV	RadioRA2 RRD-6NA	nSP5 PCD ELV 120	ISD 400 ELV 120/IPE04
6615-P	Gen 3.0 DVCL-153P (T9)	HomeWorks HQRD-6NA		
	Maestro MSCL-OP153M	Panel Module HW/LP-RPM-4A-120		
	Caseta Wireless PD-6WCL	Panel Module HW/LP-RPM-4U-120		
	Grafik T GT-5NEM / GTJ-5NEM	Grafik QS/Wallbox LQRJ-WPM-6P		
	Diva/Skylark DVRP-253PCTRP-253P	Grafik Eye 3000 Family HWI-WPM-6D-120		
	Skylark CTCL-150	HomeWorksQS / my Room LQSE-4A1-D/MQSE-4A1-D/MQSE-3A1/MQSE-2A1-D,120V		
	Caseta Wireless PD-5NE	Homeworks QS LQSE-4A-120-D		

*Requires Lutron Smart Bridge L-BDG2-WH (sold separately)

Wafer Gimbals

WF3 ADJ, WF4 ADJ, WF6 ADJ

Lutron	Leviton	Synergy/Leviton	Sensorswitch
DVELV-300P	6633	ISD 400 ELV 120 / IPE04	nSP5 PCD ELV 120
300P SELV	6674	ISD 600 I 120 / IPI06	
CTCL-153P-WH	IPL06 - LED/INC mode		
NTELV-300P	DW6HD		
DVCL-153P			
MACL-153M			
TGCL-153PH			
6633-PA			
Maestro MACL-153M (TX)			
Caseta Wireless PD-6WCL*			

* Require Lutron Smart Bridge L-BDG2-WH (sold separately) for wireless connection