

Dimmer Compatibility for 120V Wafers

MVOLT wafers are compatible with any 0-10V dimmer

Static & Switchable White Wafers

WF3, WF4, WF6, WF8

| Leviton | Lutron | | Sensorswitch | Synergy/Leviton |
|--------------------|---------------------------------|---|------------------|-----------------------|
| 6633-PA | Maestro MACL-153M (TX) | Maestro MACL-LFQ | nSP5 PCD 2W | ISD 600 I 120/IPI06 |
| IPL06-LED/INC mode | Maestro Wireless MRF2-6ELV | RadioRA2 RRD-6NA | nSP5 PCD ELV 120 | ISD 400 ELV 120/IPE04 |
| 6615-P | Gen 3.0 DVCL-153P (T9) | HomeWorks HQRD-6NA | | |
| | Maestro MSCL-OP153M | Panel Module HW/LP-RPM-4A-120 | | |
| | Caseta Wireless PD-6WCL | Panel Module HW/LP-RPM-4U-120 | | |
| | Grafik T GT-5NEM / GTJ-5NEM | Grafik QS/Wallbox LQRJ-WPM-6P | | |
| | Diva/Skylark DVRP-253PCTRP-253P | Grafik Eye 3000 Family HWI-WPM-6D-120 | | |
| | Skylark CTCL-150 | HomeWorksQS / my Room LQSE-4A1-D/ MQSE-4A1-D/MQSE-3A1/MQSE-2A1-D,120V | | |
| | Caseta Wireless PD-5NE | Homeworks QS LQSE-4A-120-D | | |

*Requires Lutron Smart Bridge L-BDG2-WH (sold separately)

Wafer Gimbals

WF3 ADJ, WF4 ADJ, WF6 ADJ

| Lutron | Leviton | Synergy/Leviton | Sensorswitch |
|--------------------------|----------------------|-------------------------|------------------|
| DVELV-300P | 6633 | ISD 400 ELV 120 / IPE04 | nSP5 PCD ELV 120 |
| 300P SELV | 6674 | ISD 600 I 120 / IPI06 | |
| CTCL-153P-WH | IPL06 - LED/INC mode | | |
| NTELV-300P | DW6HD | | |
| DVCL-153P | | | |
| MACL-153M | | | |
| TGCL-153PH | | | |
| 6633-PA | | | |
| Maestro MACL-153M (TX) | | | |
| Caseta Wireless PD-6WCL* | | | |

* Require Lutron Smart Bridge L-BDG2-WH (sold separately) for wireless connection