

90+ LIGHTING



MODEL	PAR30 12W 850LM 2700K E26
SKU	SE-RL6.CE11.1412G

DIMMER COMPATIBILITY LIST				
MANUFACTURER	BRAND	DIMMER MODEL	COMPATIBILITY	
LUTRON	DIVA	DV-603P	OK	
		DVWCL-153PH-WH	OK	
		DVW-600PH-WH	NC	
		DV-603PH-WH	OK	
		DV-600PH-WH	NC	
		DVCL-153PH	NC	
		DVCL-153P-WH	OK	
		DVWCL-153PH-WHC	OK	
		DV-600P-WH	NC	
		DVCL-253PH	NC	
		DVELV-300P-WH	OK	
		SKYLARK	CTCL-153P-WH	OK
			S-600PR-WH	NC
			S-603PGH-WH	NC
			S-600H-WH	OK
	S-10PH		NC	
	SCL-153P-WH		NC	
	S-600-IV		NC	
	S-603PH-WH		OK	
	S-600P-WH		NC	
	SCL-153PH-WH		OK	
	S-603P-WH		OK	
	SELV-300P-WH		OK	
	SLV-600-WH		OK	
	D-600PH-DK		NC	
	MAESTRO		MAW-600	NC
		MAW-600H-AL	NC	
		MACL-153M-WH	NC	
		MACL-153MR-WH	NC	
		MACL-153MH-WH	NC	
		MSCL-OP153MH-WH	NC	
		MACL-153MLH-WH	NC	
		TG-603PGH-WH	NC	
		MAELV-600-WH	OK	
		DV-603PR	NC	
		D-600RH-DK	OK	
		TOGGLER	TG-600PH-WH	NC
			TGCL-153PH-WH	OK
			D-600R-WH	OK
		D-600R-IV	OK	
	ARIADNI	AYCL-153P-WH	OK	
		AY-600PH-WH	NC	
		AYCL-153PH	OK	
	VIVE	MRF2S-6CL-WH	OK	
	CASETA	PD-6WCL-WH	OK	
	SPACER	SPSELV-600M	OK	
	NOVA T	NTELV-300-WH	OK	
	RADIO RA2	NTLV-600-277-WH	OK	
	DECORA	RRD-6CL-WH	OK	
	LEVITON	R62-6674-POW	OK	
6684		NC		
NO.6683		NC		
6631-LA		OK		
IPI06		NC		
NO.6672		NC		
603-6631-A		OK		
6631-A		OK		
NO.IPL06		NC		
IPI10-1LZ		NC		
6683-10Z		NC		
IPI06-1LZ		NC		
NO.6631		OK		
6681		NC		
18024		NC		
GE	LUXDM600-12	NC		
ALMOND	DM600-12-3	OK		
CTL	SDM3/1000	OK		
AH	SDM/600	OK		
LEGRAND	HCL453PTC	NC		
COOPER	DAL06P-C2-K	NC		
	TAL06P-C2-K	NC		
	SAL06P-W-K	NC		
MAXXIMA	AAL06-C1	NC		
	MEW-DM600	OK		

DIMMER COMPATIBILITY

OK
OK
NC

Dims to < 15%
 Dims to 15 - 30%
 Not Compatible

90+ LIGHTING NOTES

- 1) This dimmer compatibility chart is provided by 90+ Lighting as a guidance for selecting a dimmer and lamp combination.
- 2) The results may be different for each application depending on the installation conditions.
- 3) 90+ Lighting recommends to perform a previous test before the installation to verify the dimmer compatibility.
- 4) We recommend using a 1/5 loading factor for incandescent dimmers when using with 90+ lamps.
 For example: a 400W dimmer should be loaded with a number of lamps whose combined power do not exceed 80W.