NTH-106

PAR30 Roundback Cylinder with Black Baffle Lamp: 75W PAR30 max.

Туре	
Project	
Catalog No.	
Notes	

PRODUCT DESCRIPTION

Line voltage cylindrical housing with round back design and black baffle. A structural arm provides full adjustment of light source for special aiming and completely conceals wire lead from socket to contact head. Internal mechanism allows for adjustment and resists angle degradation.

FEATURES

- · Die cast aluminum provides superior strength and rigidity
- \cdot Black baffle eliminates glare and adds finished touch
- · One or two circuit track capable
- · Accepts LED lamps

CONSTRUCTION

Housing: Deep drawn steel construction with simple, yet decorative design. All edges are softened for aesthetic appearance

Baffle: Black finished phenolic high heat rated plastic baffle, provides finished appearance and assists in eliminating glare from housing interior.

Structural Arm: Extruded aluminum arm connects fixture housing to electrical contact head. Internal tightening mechanism maintains desired lamp aiming angles. Structural arm also functions as wire way, completely concealing lead wire from socket to contact head.

ELECTRICAL

Voltage: 120V input **Socket:** Medium base

Lamp: 75W PAR30 max. (not included)

ONE/TWO CIRCUIT CONVERSION

Positive contact (opposite neutral and ground contacts) is preset to "down" position at factory but may be raised to the higher position to install onto the second circuit of Nora Lighting NT- 2300 series two-circuit track.

OPTIONAL ACCESSORIES

NT-339: Black Barn Door

NT-342: Black Louver (requires NT-339 or NT-345)

NT-345: Black Accessory Holder

LABELS AND LISTINGS

UL Listed



PRODUCT IMAGES AND DIMENSIONS




NTH-106B/A



NTH-106BZ



NTH-106W/A



PAR30 Roundback Cylinder with Black Baffle

Catalog No.	Finish	Style	Max. Wattage
NTH-106	B/A = Black	(blank) = H-style	(blank) = 75W
	BZ = Bronze (While Supplies Last)	/J = J-style	/15 = 15W
	W/A = White	/L = L-style	

Optional Accessories

Description

NT-339 = Black Barn Door

NT-342 = Black Louver (requires NT-339 or NT-345)

NT-345 = Black Accessory Holder

Example: NTH-106B/A = PAR30 Roundback Cylinder with Black Baffle, Black Finish, H-Style Adapter

