















Dimmer Compatibility Chart on OVEDRRIVE Dimmable LED lamps

No.	Dimmer Maker	IMAGE														
		Overdrive Item #	501/548/551	502 / 506	503	504	505	514/524	517	525	528 / 529	526/527	538/539	540/541	542/543	546/547
		Overdrive Model #	A TYPE 5/6W 30/50K	A TYPE 8W 30K/50K	PAR20 8W 30K	PAR30 13W 30K	PAR38 20W 30K	R30 11W 30K/50K	CANDLE 3.5W E12 BASE 30K	R20 8W 30K	R40 13W 30K50K	R40 18W 30K50K	A Type 10W 30/50K	L4MRGUDIM/ FL/30K/50K	L6MRGUDIM/ FL/30K/50K	CANDLE 3/5W E12 BASE 27K
1-1	LEVITON	C20-6683-IW	√	√	√	√	√	√	√	√	√	√	√	√	√	√
1-2		C20-6681-IW	√	√	√	√	√	√	√	√	√	√	√	√	√	√
1-3		RPI06-1LI	√	√	√	√	√	√	√	√	√	√	√	√	√	√
1-4		6674-10W	√	√	√	√	√	√	√	√	√	√	√	√	√	√
1-5		6615-POW	×	×	×	√	√	√	×	×	√	√	√	×	×	√
1-6		R15-IPI06-1SE	√	√	√	√	√	√	√	√	√	√	√	√	√	√
1-7		010-IPE04-1LZ	×	√	√	√	√	√	×	√	√	√	√	×	√	√
1-8		R50-6602-IW	√	√	√	√	√	√	√	√	√	√	√	√	√	√
2-1	LUTRON	TTCL-100H-WH	√	√	√	√	√	√	√	√	√	√	√	√	√	√
2-2		D-600PH-DK	√	√	√	√	√	√	√	√	√	√	√	√	√	√
2-3		DVLV-600P-WH	√	√	√	√	√	√	√	√	√	√	√	√	√	√
2-4		NTLV-600-WH	√	√	√	√	√	√	√	√	√	√	√	√	√	√
2-5		DVELV-300P-WH	√	√	√	√	√	√	√	√	√	√	√	√	√	√
2-6		DV-603PG-WH	√	√	√	√	√	√	√	√	√	√	√	√	√	√
2-7		NLV-600-WH	√	√	√	√	√	√	√	√	√	√	√	√	√	√
2-8		CTCL-153PDH	√	√	√	√	√	√	√	√	√	√	√	√	√	√
2-9		D-603PH	√	√	√	√	√	√	√	√	√	√	√	√	√	√
2-10		TT-300NLN-WH	√	√	√	√	√	√	√	√	√	√	√	√	√	√
2-11		MRF2-3PD-1-1WH(Digital)	√	√	√	√	√	√	√	√	√	√	√	√	√	√
2-12		MA-600-WH(Digital)	×	×	×	×	×	×	×	×	×	×	×	×	×	×
2-13		MAW-600(Digital)	×	×	×	×	×	×	×	×	×	×	×	×	×	×
2-14		MRF2-6ND-120-WH(Digital)	√	√	√	√	√	√	√	√	√	√	√	√	√	√
2-15	RRD-10ND-WH(Digital)	√	√	√	√	√	√	√	√	√	√	√	√	√	√	
2-16	VTELV-600M-B-WH(Digital)	√	√	√	√	√	√	√	√	√	√	√	√	√	√	
2-17	MAELV-600-WH(Digital)	√	√	√	√	√	√	√	√	√	√	√	√	√	√	
2-18	MRF2-6ELV-120-WH(Digital)	√	√	√	√	√	√	√	√	√	√	√	√	√	√	
2-19	TG-603PGH-WH	√	√	√	√	√	√	√	√	√	√	√	√	√	√	
2-20	AYLV-600P-WH	√	√	√	√	√	√	√	√	√	√	√	√	√	√	
2-21	TG-603PGH-WH	√	√	√	√	√	√	√	√	√	√	√	√	√	√	
2-22	S-600PR-WH	√	√	√	√	√	√	√	√	√	√	√	√	√	√	
3-1	LEGRAND	DRD4-B(Digital)	√	√	√	√	√	√	√	√	√	√	√	√	√	√
4-1	PASS & SEYMOUR	CD703-PW	√	√	√	√	√	√	√	√	√	√	√	√	√	√
4-2		CDLV703-P	√	√	√	√	√	√	√	√	√	√	√	√	√	√
4-3		D703-PTC	√	√	√	√	√	√	√	√	√	√	√	√	√	√
4-4		DLV703-P	√	√	√	√	√	√	√	√	√	√	√	√	√	√

Note: This document is property of "OVERDRIVE Electronics Pvt. Ltd" and should not be copied without written permission. This data sheet is not controlled copy & is subject to change without notice. 07/2013