



WORLDWIDE PARTNER

Commercial Products & Solutions

SITE SEARCH > HOME ** PRODUCTS > EDUCATION / RESOURCES > LIGHTING APPLICATIONS


Where to Buy | FAQs | Contact Us | EliteNet

<u>Products</u> > 97596

97596 - F13DBX/835/ECO4P

GE Ecolux® Biax® T4 - Facilities; Retail Display; Hospitality; Office; Restaurant; Warehouse





Lamp type	Compact Fluorescent - Plug-In
Bulb	T4
Base	G24q-1
Wattage	13
Voltage	91
Rated Life	12000 hrs/20000 hrs
Starting Temperature (MIN)	0 ℃ (32 ℉)
Cathode Resistance	10.500 Ohm
LEED-EB MR Credit	442 picograms Hg per mean lumen hour
Additional Info	Dimmable with appropriate dimming ballast., End of Life Protection (EOL), TCLP compliant
Primary Application	Facilities; Retail Display; Hospitality; Office; Restaurant; Warehouse

PHOTOMETRIC CHARACTERISTICS

Initial Lumens	900
Mean Lumens	755
Nominal Initial Lumens per Watt	69
Color Temperature	3500 K
Color Rendering Index (CRI)	82

ELECTRICAL CHARACTERISTICS

Current (max)	5.2500 A			
Open Circuit Voltage (after preheating) (MAX)	190 V			
Open Circuit Voltage Across Starter (MIN)	198 V			
Lamp Current	0.175 A			
Preheat Voltage (MIN)	4 V			
Current Crest Factor (MAX)	1.7			
Supply Current	60 Hz			







View Larger


ADDITIONAL RESOURCES

Catalogs Testimonials

<u>Disposal Policies & Recycling Information</u>

GRAPHS & CHARTS

Spectral Power Distribution



Frequency

DIMENSIONS	
Maximum Overall Length (MOL)	4.9000 in (124.4 mm)
Nominal Length	5.000 in (127 mm)
Base Face to Top of Lamp	4.400 in (111.7 mm)

PRODUCT INFORMATION

Product Code	97596
Description	F13DBX/835/ECO4P
ANSI Code	60901-IEC-2513-2
Standard Package	BUNDLE
Standard Package Quantity	50
Sales Unit	Unit
No Of Items Per Sales Unit	1
No Of Items Per Standard Package	50
UPC	043168975964

COMPATIBLE GE BALLASTS

Product Code	Description	# of Bulbs	Power Factor	Ballast Factor		
80669	C213UNVBE- IP	1	98.0	1.0		
71430	GEC213- MVPS-3W	1	96.0	1.0		
71428	GEC213- MVPS-BES	1	96.0	1.0		
71429	GEC213- MVPS-SE	1	96.0	1.0		

A CAUTIONS & WARNINGS

See list of cautions & warnings.

NOTES

- 4-Pin lamp minimum starting temperature is a function of the ballast. Most ballasts are rated with a minimum starting temperature of 50 degrees F (10 C). Ballasts are also available that provide reliable starting to 0 degrees F (-18C) and -20 F (-29C).
- Based on 60Hz reference circuit.
- Fluorescent lamp lumens decline during life

Return To Top

Home | Products | EliteNet | Education/Resources | Lighting Applications | Where to Buy | FAQs | Contact Us | Site Map
Products for Your Home | Press Room | Corporate | Investor Information | Privacy Policy | Accessibility Statement | Terms of Use
Copyright General Electric Company 1997-2009