

WORKS WITH SORAA

SORAA-TESTED DIMMER & TRANSFORMER COMBINATIONS

| Electronic Transformers | Trailing Edge Dimmers | Lutron | Lutron | Lutron | Lutron | Lutron | Leviton | Marlin |
|-------------------------|-----------------------|-----------------|----------------|-------------------|------------------|-------------------|----------------|---|
| | Model | Diva DVELV-300P | SPSELV-600 | Maestro MAELV-600 | Nova T NTELV-300 | Skylark SELV-300P | 6615-P 300W | Stellar DIMMING CABINET P/N 6-3-08-20-3-103T with RMS |
| Hatch | RS12-60M | 9% | 26% | 11% | 13% | 10% | Not Compatible | 9% |
| Hatch | VS12-60 | 7% | 24% | 13% | Not Compatible | 8% | 32% | 0% |
| Hatch | VS12-60WD | 8% | 17% | 12% | 15% | 9% | 24% | 6% |
| Hatch | VS12-75WD | 8% | 23% | 13% | 14% | 9% | 24% | Not Compatible |
| Hatch | VS12-105 | Not Compatible | Not Compatible | Not Compatible | Not Compatible | Not Compatible | Not Compatible | Not Compatible |
| Hatch | VS12-150 | 9% | 19% | 14% | 15% | 10% | 44% | Not Compatible |
| Lightech | LET 60 | 6% | 23% | 9% | 14% | 8% | 41% | 16% |
| Lightech | LET 75 | 5% | 21% | 10% | 10% | 6% | 41% | 15% |
| Lightech | LET 105 | 7% | 12% | 12% | 13% | 8% | 31% | 9% |
| Lightech | LET 151 R LDC | 6% | Not Compatible | Not Compatible | 51% | Not Compatible | 82% | 8% |
| Lightech | 303 AC 120 12 | 9% | 16% | 16% | 17% | 11% | 24% | 10% |
| B+L | CV90021 | 10% | 17% | 16% | 17% | 12% | 37% | N/A |
| B+L | FX95100 | 9% | 14% | 13% | 15% | 10% | 63% | N/A |
| B+L | MS90119 | Not Compatible | 21% | 13% | Not Compatible | N/A | N/A | N/A |
| B+L | CV-10/75-12 | 10% | 19% | 12% | 16% | 11% | 29% | N/A |

| Magnetic Transformers | Leading Edge Dimmers | Lutron | Lutron | Lutron | Lutron | Marlin |
|-----------------------|-------------------------------------|--------------------------|-------------------|----------------|-----------------|---|
| | Model | Grafik Eye #3000 | Skylark SL V-600P | Diva DVLV-600P | Ceana CNLV-600P | Stellar DIMMING CABINET P/N 6-3-08-20-3-103T with RMS 8 Control Unit - approx. 6 Kilo-Watts Total |
| Cooper | TF-149911 | 35% | 24% | 29% | 26% | 9% |
| Cooper | TF 149911-TP120 | 39% (Ventilated fixture) | 24% | N/A | 25% | 9% |
| Linea | 701970 | 40% (Ventilated Fixture) | 26% | 32% | 28% | 9% |
| Hasler Electric | MI-5481E | 37% (Ventilated Fixture) | N/A | N/A | N/A | 9% |
| Juno | 310-1333 | 39% | 23% | N/A | N/A | 8% |
| Orientronic | DLR1250BN | N/A | N/A | N/A | N/A | 8% |
| Q-TRAN | QT-50-75CK-PT-BLK-4 | N/A | N/A | N/A | N/A | Not Compatible |
| Q-TRAN | QT50SV-120/12-RC | N/A | N/A | N/A | N/A | 8% |
| Q-TRAN | QT20-120/12-TP-RC | N/A | N/A | N/A | N/A | 9% |
| Q-TRAN | QT10-120/12-TP-RC | N/A | N/A | N/A | N/A | 8% |
| Q-TRAN | Q6S-DC-120-12 (Rectified) | N/A | N/A | N/A | N/A | 10% |
| Q-TRAN | QTM60-DC+CAP (Rectified + Filtered) | N/A | N/A | N/A | N/A | 19% |

WORKS WITH SORAA

WORKS WITH SORAA TRANSFORMERS

| Manufacturer | Model | Type | Indoor | Outdoor |
|--------------|------------|----------|-------------------------|---------|
| Q-TRAN | QTMD | Magnetic | Y | |
| Q-TRAN | QTMS | Magnetic | Y | |
| Q-TRAN | QTM-ST | Magnetic | Y | |
| Q-TRAN | QTMD-ST | Magnetic | Y | |
| Q-TRAN | QTLS | Magnetic | Y | |
| Q-TRAN | QTLD | Magnetic | Y | |
| Q-TRAN | QTLT | Magnetic | Y | |
| Q-TRAN | QTLQ | Magnetic | Y | |
| Q-TRAN | QTLS-ST | Magnetic | Y | |
| Q-TRAN | QTLD-ST | Magnetic | Y | |
| Q-TRAN | QTLT-ST | Magnetic | Y | |
| Q-TRAN | QTLQ-ST | Magnetic | Y | |
| Q-TRAN | Q6S | Magnetic | Y | |
| Q-TRAN | Q6M | Magnetic | Y | |
| Q-TRAN | Q6L | Magnetic | Y | |
| Q-TRAN | QT-10 | Magnetic | Y (Integral to Fixture) | |
| Q-TRAN | QT-20 | Magnetic | Y (Integral to Fixture) | |
| Q-TRAN | QT-50-75 | Magnetic | Y (Integral to Fixture) | |
| Q-TRAN | Q-SET-1 | Magnetic | | Y |
| Q-TRAN | Q-SET-2 | Magnetic | | Y |
| Q-TRAN | Q-SET-3 | Magnetic | | Y |
| Q-TRAN | Q-HEX-MINI | Magnetic | | Y |
| Q-TRAN | Q-HEX | Magnetic | | Y |
| Q-TRAN | QOMS | Magnetic | | Y |
| Q-TRAN | QOMD | Magnetic | | Y |

SORAA-TESTED TRANSFORMERS, NORTH AMERICA

| Input Voltage | Manufacturer | Model | Wattage | Transformer Type | 1 Lamp | 2 Lamps | 3 Lamps |
|---------------|-------------------------|---|---------|------------------|----------------|----------------|----------------|
| 120VAC | B+L | CV90001 (CV-10/75-12) | 10-75W | Electronic | Pass | Pass | Pass |
| 120VAC | B+L | CV90010 | 10-105W | Electronic | Pass | Pass | Pass |
| 120VAC | B+L | CV90012 | 10-150W | Electronic | Pass | Pass | Pass |
| 120VAC | B+L | CV90021 | 10-200W | Electronic | Pass | Pass | Pass |
| 120VAC | B+L | FX95100 | 0-75W | Electronic | Pass | Pass | Pass |
| 120VAC | B+L | MS90117 | 35-75W | Electronic | Not Compatible | Not Compatible | Not Compatible |
| 120VAC | B+L | MS90119 | 35-75W | Electronic | Pass | Pass | Pass |
| 120VAC | B+L | LS94117 | 75 | Electronic | Not Compatible | Not Compatible | Pass |
| 120VAC | Hatch | RS12-60 (any suffix) | 60W | Electronic | Pass | Pass | Pass |
| 120VAC | Hatch | RS12-15M/30M/60M-LED (any suffix) | 60W | Electronic | N/A | N/A | N/A |
| 120VAC | Hatch | RS12-80 (any suffix) | 80W | Electronic | Pass | Pass | Pass |
| 120VAC | Hatch | VS12-150 | 150W | Electronic | Not Compatible | Not Compatible | Not Compatible |
| 120VAC | Hatch | RS12-150W | 150W | Electronic | Pass | Pass | Pass |
| 120VAC | Hatch | RS12-300W | 300W | Electronic | Pass | Pass | Pass |
| 120VAC | Hatch, Juno | Hatch VS12-60W (Juno TL544N) (any suffix) | 60W | Electronic | Pass | Pass | Pass |
| 120VAC | Hatch, Juno | Hatch VS12-60W (any suffix) | 60W | Electronic | Pass | Pass | Pass |
| 120VAC | Hatch, Juno | Hatch VS12-75W (any suffix) | 75W | Electronic | Pass | Pass | Pass |
| 120VAC | Hatch, Juno | Hatch VS12-105W (any suffix) | 105W | Electronic | Not Compatible | Pass | Pass |
| 120VAC | Lightech, Cooper RSA | Lightech LET-60 (RSA RT-60) | 60W | Electronic | Pass | Pass | Pass |
| 120VAC | Lightech, Cooper RSA | Lightech LET-75 (RSA RT-75L) | 75W | Electronic | Pass | Pass | Pass |
| 120VAC | Lightech, Cooper RSA | Lightech LET-105W (RSA RT-105) | 105W | Electronic | Pass | Pass | Pass |
| 120VAC | Lightech, Cooper RSA | Lightech LET-151 (RSA RT-150) | 150W | Electronic | Not Compatible | Not Compatible | Not Compatible |
| 120VAC | Lightech, Cooper RSA | Lightech LET-303-12 (RSA RT-300L) | 300W | Electronic | Pass | Pass | Pass |
| 120VAC | Lightech, Cooper RSA | Lightech LET-60-LW | 60W | Electronic | Not Compatible | Not Compatible | Not Compatible |
| 120VAC | LTF / Generation Brands | TA60WA12LED / 250LED60W | 60W | Electronic | Pass | Pass | Pass |
| 230VAC | LTF / Generation Brands | TU75WA12LED / 250TU75WA12LED | 75W | Electronic | Pass | Pass | Pass |
| 230VAC | LTF / Generation Brands | TU150WA12LED / 250TA150WA12LED | 150W | Electronic | Not Compatible | Pass | Pass |
| 120VAC | ELG | 25OLT2512 | 75W | Electronic | Not Compatible | Pass | Pass |
| 120VAC | LTF | TA60WA12LED-0000 | 60W | Electronic | Pass | Pass | Pass |
| 120VAC | MDL-Corp | 316-0002 | 150W | Electronic | Pass | Pass | Pass |
| 120VAC | PONY | PET-120-12-75 | 75 | Electronic | Pass | Pass | Pass |
| 120VAC | RSA | RT60A | 60 | Electronic | Pass | Pass | Pass |
| 120VAC | WAC | EN-12100-R-AR | 100 | Electronic | Pass | Pass | Pass |
| 120VAC | Juno | 310-1333 | 300VA | Magnetic | Pass | Pass | Pass |
| 120VAC | Basler Electric | MI-5481E | 50VA | Magnetic | Pass | Pass | Pass |
| 120VAC | Cooper | TF149911-TPI20XFMR | 50VA | Magnetic | Pass | Pass | Pass |
| 120VAC | Cooper | TF-149911 | 50VA | Magnetic | Pass | Pass | Pass |
| 120VAC | LINEA | 701970 | 300VA | Magnetic | Pass | Pass | Pass |