



## SORAA LED MR16 120v GU10 base Dimming

Manufacturer	Brand	MD #	Dimmer Type (Leading/Trailing)	Dim (%)			Flicker (Y/N)	Maximum # of lamps
				1 lamp	2 lamps	3 lamps		
Lutron	DIVA	DV-600P	L	15%	21%	21%	N	13 lamps
Lutron	Rotary	D0603PGH-DK	L	23%	23%	23%	N	13 lamps
Lutron	Skylark	CTCL-153P	L	20%	20%	20%	N	6 lamps
Lutron	Skylark	CT-600P	L	21%	21%	21%	N	13 lamps
Lutron	Skylark	S-600	L	14%	14%	14%	N	13 lamps
Lutron	Skylark	S-603PG	L	29%	29%	29%	N	13 lamps
Lutron	Skylark	SLV-600P	L	22%	22%	22%	N	13 lamps
Lutron	Skylark	SELV-300P	T	18%	18%	18%	N	6 lamps
Lutron	Nova	NTELV-300	T	26%	26%	26%	N	6 lamps
Lutron	MAESTRO	MACL-153M	L	26%	26%	26%	N	6 lamps
Lutron	MAESTRO	MRF2-6ND-120	T	27%	27%	27%	N	8 lamps
Lutron	TOGGLER	TG-600PR-WH	L	12%	12%	12%	N	13 lamps
Lutron	Glyder	GL-600G-DK	L	20%	20%	20%	N	13 lamps
Lutron	ATHENA	T-1000	L	13%	13%	13%	N	20 lamps
Lutron	Faetra	FAELV-500M	T	13%	13%	13%	N	10 lamps
Lutron	Grafik Eye	#3000	L	22%	22%	22%	N	13 lamps
Lutron	RadioRa2	RRD-10D	L	Not Compatible	Not Compatible	21%	N	20 lamps
Lightolier	Controls	ZP600	L	17%	17%	17%	N	13 lamps
Lightolier	Controls	ZP1000	L	16%	16%	16%	N	20 lamps
LEVITON	DECORA	IPL06	L	6%	6%	6%	N	6 lamps
LEVITON	DECORA	6633-P	L	14%	14%	14%	N	6 lamps
COOPER	6B28	9530	L	13%	13%	13%	N	6 lamps
COOPER	6B28	D106P	L	14%	14%	14%	N	6 lamps
COOPER	6B28	SLC03P	L	22%	22%	22%	N	6 lamps

\*The lamps when switched off at the lowest dim level, might not come on when switched on later. When this happens, the lamps can be activated by increasing the level on the dimmer.

\*\* The values listed are the lowest dim levels when dimming down

\*\*\* The values are light levels, not dimmer range levels or power levels

\*\*\*\* The values have been tested from 108V to 132V