Titanium Series 3.0 MR16 7W High CRI #01-721-D

Magnetic Dimmer Switch Compatibility

GREEN CREATIVE

Brand	Series	Model	Load	HALO CAN — H1499ICAT / H36LVRTAY / H1499TAT / H149RTAT (1–4)	ELCO CAN — EL1499ICA / EL1499S / EL1499 / EL1499R (1–5)	NORA CAN — NLR-404/75/277V (1–3)	JUNO CAN — TC44R / IC44N (1–2)	ELG transf. — BBC1ZA-B02XCI-2500X (1–6)	ESBCO transf. — 1105-12 (300W) (1–6)
LUTRON	Diva	DVLV-600P	600	OK (all columns)					
	Abella	ABLV-1000M	600	X (1–3), OK (4)	X (1), OK (2–5)	20-100% (1–2), OK (3)	X (1), 20-100% (2)	X (1), OK (2–6)	35-100% (1–3), OK (4–6)
	Maestro	MALV-600	600	X (1–3), OK (4)	X (1–3), OK (4–5)	X	X (1), OK (2)	X	X
	Maestro	MALV-1000	1000	X (1–3), OK (4)	X (1), 20-100% (2–5)	X (1), 20-100% (2–3)	X (1), 20-100% (2)	25-100% (1), OK (2–6)	X (1–3), OK (4–6)
	Lyneo LX	LXLV-600PL	600	25-100%	15-100%	15-100%	25-100%	15-100%	15-100%
	Skylark	SLV-600P	600	25-100%	10-100%	15-100%	25-100%	10-100%	10-100%
	Toggler	TGLV-600PR	600	OK	OK	OK	OK	OK (1), 25-100% (2–6)	25-100%
LEVITON	Sure Slide	6613-PLA	600	25-100%	15-100%	15-100%	25-100%	15-100%	30-100%
	Vizia +	VPM10-1LZ	600	25-100%	20-100%	15-100%	25-100%	25-100%	30-100%
COOPER	Aspire	9536WS	1000	X (all columns)					

Table Key
OK = Fully compatible
__-__% = Compatible within this range, flicker outside the range
X = Incompatible

*GREEN CREATIVE has provided this dimmer switch compatibility chart for guidance when selecting a dimmer and lamp combination. Our lamps were tested for compatibility with the above listed dimmers. Dimmers that do not appear on the chart might still be compatible but have not been tested. All testing has been performed with a stable main supply. The quality of the local main, existing installation and wiring, as well as different manufacturer versions of the above dimmers and transformers may affect dimming performance. Since no assurance can be provided regarding these factors, it is a general recommendation to perform a test on-site prior to installing the LED lamps.

Titanium Series 3.0 MR16 7W High CRI #01-721-D

Electronic Dimmer Switch Compatibility

GREENCREATIVE

Brand	Series	Model	Load	Dimmability (# of lamps)																															
				Hatch																		Lightech						ELCO				WAC		SATCO	
				RS 12-60M						RS 12-80M						RS 12-60M (LED)						LRT60						Track				Track		Track	
				1	2	3	4	5	6	1	2	3	4	5	6	1	2	3	4	5	6	1	2	3	4	5	6	1	2	3	4	1	2	1	2
LUTRON Skylark	Skylark	SELV-300P	300	OK						OK						OK		25-100%				OK						Flickers at 35%				X		OK	
	Diva	DVELV-300P	300	OK						OK						OK		25-100%				OK						Flickers at 50%				X		OK	
LEVITON	Sure Slide	6615-P0W	300	OK						OK						X						OK						OK	X			X		OK	

Table Key
OK= Fully compatible
__-__% = Compatible within this range, flicker outside the range
X= Incompatible

*GREEN CREATIVE has provided this dimmer switch compatibility chart for guidance when selecting a dimmer and lamp combination. Our lamps were tested for compatibility with the above listed dimmers. Dimmers that do not appear on the chart might still be compatible but have not been tested. All testing has been performed with a stable main supply. The quality of the local main, existing installation and wiring, as well as different manufacturer versions of the above dimmers and transformers may affect dimming performance. Since no assurance can be provided regarding these factors, it is a general recommendation to perform a test on-site prior to installing the LED lamps.