





Cautions and Warnings 90W Replacement Cree PAR38 LED Bulbs

- Not intended for use with emergency exit fixtures or emergency lighting.
- Risk of electric shock or burns. Turn power off and let cool before inspection or replacement. Do not open – no user serviceable parts inside. Use only on 120 volt AC circuits.
- Do not use if outer glass is cracked, broken or missing, even if lamp continues to light.
- Lifetime may be reduced if used in air tight enclosures or in insulated ceiling air tight (ICAT) recessed down light enclosures.
- Suitable for use in operating environments between -35°C and +45°C (-31°F and +113°F).
- Suitable for wet locations where exposed directly to weather
- This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.